

Lightology

lightology.com
866-954-4489
07-29-26

Project: _____

Company: _____

Location: _____ Fixture Type: _____

SPEC #: **TLG9451**

Approved On: _____ Approved By: _____


300W 12V Remote Electronic Transformer

By Visual Comfort Modern



Description

This 300 watt 12 volt remote electronic transformer converts standard 120 line voltage to 12 volts, providing the necessary voltage for powering a Monorail, Kable Lite, Wall Monorail or Freejack low voltage lighting system. Can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting short circuit and overload protection that will safely turn off the system should a short occur. Once the short is removed, the unit can be reset by simply flipping the wall switch off and back on. Must be installed in a remote, but accessible location such as above the ceiling or in a closet, and should be located no more than 20 feet from the required single feed power feed, sold separately. 8.5 inch length x 3.5 inch width x 2 inch height.



Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	300W
DIMMER	Low Voltage Electronic
DIMENSIONS	8.5"L x 3.5"W x 2"H
BULB	N/A

Notes:

--