



BRAND Visual Comfort Modern


DESCRIPTION

This 300 watt 12 volt remote electronic transformer converts standard 120 volt line-voltage to 12 volts, providing the necessary voltage for powering a Monorail, Kable Lite, Wall Monorail or FreeJack low-voltage lighting system. Includes 16 foot cord with plug. Can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting short circuit and overload protection that will safely turn off the system should a short occur. Once the short is removed, the unit can be reset by simply flipping the wall switch off and back on. Must be installed in a remote, but accessible location such as above the ceiling or a closet, and should be located no more than 20 feet from the required single feed power feed, sold separately. ETL listed. 8.5 inch length x 3.5 inch width x 2 inch height.



SHADE COLOR	N/A
BODY FINISH	Black
WATTAGE	300W
DIMMER	Low Voltage Electronic
DIMENSIONS	8.5"L x 3.5"W x 2"H
LAMP	N/A

SPEC # TLG9456



COMPANY	PROJECT	FIXTURE TYPE	APPROVED BY	DATE