




T-600-24



Description:

The 600 Watt 24 Volt Magnetic Remote Mount Transformers convert line voltage into 24 volt power and are protected by fast-acting circuit breakers. The safe-to-touch low voltage output powers Monorail systems up to 600 watts using 24 volt lamps.

Power Input:

120 volts AC 2.5 Amp
230 volt AC 1.3 Amp
277 volt AC 1.1 Amp

Power Output:

24 volts AC 600 watt 25 Amp

Installation:

Remote magnetic transformers must be installed in an accessible location, such as an attic or in a closet, up to 20 feet from the power feed canopy. Plug in version available.

Dimming:

1000 Watt Magnetic Low Voltage Dimmer. Compatible dimmers are connected on the line voltage side of transformers. Some buzzing may occur at low levels and may be reduced with a de-buzzing coil.

Dimensions:

9.5"(L) x 6"(D) x 4.75"(H)
(24.13cm x 15.24cm x 12cm)

Weight:

8.41 lb (3.81 kg)

Ordering Code:

T	-	600-24	-	Standard 120V (leave blank)
T Remote Transformer		600-24 600 Watt 24 Volt		2 230V 50Hz 3 277V 60Hz P Plug-In

Low Voltage Feed Wire Size Chart

To determine the correct THHN wire sizes for a recommended 3% or less drop in voltage for each circuit based on the specified wattage. Lengths are the distance from the remote transformer to the system power feed connector, or power supply.

24 VOLT	5 ft.	6-15 ft.	16-20 ft.	21-40 ft.
600 watt	#10 GA	#8 GA	#6 GA	#4 GA

Compatible Power Feed Canopies						
<input type="checkbox"/>		MP - 4RD MP Monorail Power Feed 4" Round Canopy	-	1 1 1" (2.5cm) 6 6" (15.2) 12 12" (30.5cm) 24 24" (61cm) 36 36" (91.4cm) 48 48" (122cm) 96 96" (243.8cm)	-	SN SN Satin Nickel PN Polished Nickel BZ Antique Bronze
<input type="checkbox"/>		MP - 4RD MP Monorail Power Feed 4" Round Canopy	-	A A 12' (3.7m) Adjustable Cable	-	SN SN Satin Nickel PN Polished Nickel BZ Antique Bronze
<input type="checkbox"/>		MP - 4RD MP Monorail Power Feed 4" Round Canopy	-	FE FE Feed End Wall	-	SN SN Satin Nickel PN Polished Nickel BZ Antique Bronze
<input type="checkbox"/>		MP - 4RD MP Monorail Power Feed 4" Round Canopy	-	ME ME Adjustable Monorail Feed End	-	SN SN Satin Nickel PN Polished Nickel BZ Antique Bronze
<input type="checkbox"/>		MP - 2SQ MP Monorail Power Feed 2" Square Canopy J-Box Included	-	1 1 1" (2.5cm)	-	SN SN Satin Nickel PN Polished Nickel BZ Antique Bronze
<input type="checkbox"/>		MP - 2SQ MP Monorail Power Feed 2" Square Canopy J-Box Included	-	FE FE Feed End Wall	-	SN SN Satin Nickel PN Polished Nickel BZ Antique Bronze

