

# LOW-VOLTAGE PENDANTS

## Sky Pendant

### DESCRIPTION

Lightweight anodized metal pendant. Available in 8" or 12" diameter. Includes low-voltage, 50 watt MR16 flood lamp or 8 watt replaceable 500 lumen 80 CRI 3000K LED SORAA® module and six feet of field-cutttable suspension cable. Works with SORAA.

### INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system.

### ACCESSORIES & OPTICAL CONTROLS


SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook

### WEIGHT

1.45lb / 0.66kg ±



copper



copper

satin nickel

### ORDERING INFORMATION

700	SYSTEM	SKY	SHAPE OR SIZE	COLOR	FINISH	LAMP
FJ	FREEJACK		12 12" DIAMETER	CP COPPER	Z ANTIQUE BRONZE	12 VOLT HALOGEN
K	KABLE LITE		08 8" DIAMETER	SN SATIN NICKEL	C CHROME	-LEDS830 12 VOLT LED 80 CRI 3000K
MP	MONOPOINT				S SATIN NICKEL	-24 24 VOLT HALOGEN
MO	MONORAIL					
MO2	TWO-CIRCUIT MONORAIL					

Note: Note: MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.

When installing LED option on MO2 only magnetic transformers may be used.



7400 Linder Avenue T 847.410.4400  
Skokie, Illinois 60077 F 847.410.4500

Tech Lighting, L.L.C.

700 \_\_\_\_ SKY \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_