



ASSEMBLY INSTRUCTIONS FOR YOUR MARCEL FLUSH MOUNT

IMPORTANT SAFETY INSTRUCTIONS:

- * These instructions are provided for your safety.
 - * It is very important that they are read completely before beginning the installation of your fixture.
 - * **WE STRONGLY RECOMMEND INSTALLATION BY A LICENSED ELECTRICIAN.**
 - * If any special control devices are used with this fixture, follow the instructions carefully to assure full compliance with N.E.C. requirements.
- If there are any questions, contact a qualified electrical contractor.

ASSEMBLY INSTRUCTIONS:

1. SHUT OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/ CIRCUIT BREAKER.
2. Remove all parts from carton and discard packing materials. Place the parts on a level surface.
3. Remove mounting plate (A) from housing (D) by removing decorative nuts (C). Remove finial (G) and washer (H) from housing (D).
4. Lift mounting plate (A) to the ceiling outlet box. Attach mounting plate (A) to ceiling outlet box using screws (B).
5. Lift housing (D) to mounting plate (A). Pull wires from ceiling outlet box through the hole in mounting plate (A).
6. Make the proper electrical connections noted in steps 7 through 9. A LICENSED ELECTRICIAN IS RECOMMENDED.
7. Attach ground wire from fixture (green or copper in color) to ground wire from outlet box. Fasten wires together with wire nut (F) and tightly wrap connection with electrical tape.
8. Attach hot wire from fixture (black in color or smooth side of wire) to hot wire from outlet box. Fasten wires together with wire nut (F) and tightly wrap connection with electrical tape.
9. Attach neutral wire from fixture (white in color or ribbed side of wire) to neutral wire from outlet box. Fasten wires together with wire nut (F) and tightly wrap connection with electrical tape. Gently push wire connections back into the ceiling outlet box.
10. Align holes in the housing (D) to the two screws on the mounting plate (A). Thread both decorative nuts (C) onto the two screws to lock housing (D) to mounting plate (A).
11. Install three 75W type A bulbs into three sockets (E).
12. Lift glass (I) to housing (D) apply plastic washer (H) to finial (G) and apply both to threaded piece on housing (D). Then align and hand tighten threaded pins (J) into all three brackets (K).
13. Lift metal shade (L) and align the three holes in metal shade (L) with threaded pins (J). Secure by applying three decorative bolts (M).
14. Reconnect main electrical supply at the fuse box/ circuit breaker and test the fixture.

