


BULBRITE

LED Retrofit Lamps

Dimmer Compatibility List



PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

8W LED R20

Model: LED8R20/27K/D

Model: LED8R20/30K/D

| | Manufacturer | Product | Model Number | Overall Rating | Lamps per Dimmer | |
|-------------------------------|--------------|-----------------|--------------|----------------|------------------|------|
| | | | | | Min | Max* |
| Incandescent/Halogen | Legrand | Titan | CD703-PW | Best | 1 | 6 |
| | | Harmony | D703-PTC | Best | 1 | 6 |
| | Leviton | SureSlide | 6633-P | Best | 1 | 6 |
| | | IllumaTech | IPI06 | Best | 1 | 6 |
| | Lutron | Divi | DV-600 | Best | 1 | 6 |
| | | Maestro | MAW-600 | Not Compatible | n/a | n/a |
| | | Skylark | S-600P | Best | 1 | 6 |
| | | | Toggler | TG600-PR | Best | 1 |
| CFL/LED Dimmers | Legrand | Harmony | DCL453-PTC | Best | 1 | 6 |
| | Leviton | Illumatech | IPL06 | Best | 1 | 6 |
| | Lutron | Skylark Contour | CTCL-153 | Best | 1 | 6 |
| | | Divi | DVCL-153PL | Best | 1 | 6 |
| | | Toggler | TGCL-153PH | Best | 1 | 6 |
| Electronic Low Voltage | Legrand | Scene Director | SECELV | Best | 1 | 6 |
| | Leviton | IllumaTech | IPE04 | Best† | 1 | 6 |
| | | Vizia | VPE04 | Best† | 1 | 6 |
| | Lutron | Skylark | SELVB-300P | Best† | 1 | 6 |
| Magnetic Low Voltage | Legrand | Titan | CDLV703-PW | Best | 1 | 6 |
| | | Harmony | DLV703-PW | Best | 1 | 6 |
| | Leviton | Vizia | VPM-06 | Best | 1 | 6 |
| Universal | Legrand | Adorne softTap | ADTP703TU | Best | 1 | 6 |
| | | Miro Decorator | DRD4-W | Best | 1 | 6 |

*Max (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible - Major flickering observed, audible noise, no dimming range

Limited - Minimal adjustment may be required, audible noise may be present, minor flickering observed but does not affect dimming range and can be removed with slight dim adjustment

Best - No flickering, minor or no audible noise, wide dimming range (20% or less light output)

Dimming Range Adjustment for Lutron C•L dimmers

1. Turn dimmer on and **move slider down to the bottom.**
2. Turn adjustment dial **up** (clockwise) until lowest light level is achieved and light output is stable for all bulbs. **Note:** If dial stops, do not continue to turn.
3. Turn dimmer off, then back on to verify bulbs turn on.
4. If all bulbs do not turn on, turn adjustment dial down (counter-clockwise) slightly and repeat step 3.
5. Once all bulbs are dimming properly, install faceplate.

Contact Information:

Bulbrite Industries Inc.
 145 W. Commercial Ave.
 Moonachie, NJ 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com

©2013 Bulbrite Industries Inc.

All Rights Reserved.

www.bulbrite.com/LED