


R3-DS88

3" SQUARE ADJUSTABLE SPOT TRIM
DIECAST



Project

Location



PRODUCT DESCRIPTION

3" Square adjustable spot trim

To be used in low and line voltage applications. Trim will adjust 35 degrees from vertical position.

LAMPING: Accommodates an MR-16 or GU-10 bulb. Please see housing for maximum wattage allowed according to selection.

Clear lens included. Steel metal clips secure to housing.

DIAMETER: 3 3/4"

FINISHES: Matte White (MW)

MODEL	FINISH
R3-DS88	MW

COMPATIBLE HOUSINGS

Model	Description
R3-050	3" LOW VOLTAGE NON IC REMODEL HOUSING REMOTE TRANSFORMER (NOT SUPPLIED)50W MAX MR-16
R3-499AT	3" LOW VOLTAGE NON IC AIRTITE NEW CONSTRUCTION HOUSING 50W MAX MR-16
R3-499ICA	3" LOW VOLTAGE IC AIRTITE NEW CONSTRUCTION HOUSING 35W MAX MR-16
R3-499RAT	3" LOW VOLTAGE NON IC AIRTITE REMODEL HOUSING 50W MAX MR-16
R3-G19AT	3" LINE VOLTAGE NON IC AIRTITE NEW CONSTRUCTION HOUSING 50W MAX GU-10
R3-G19ICA	3" LINE VOLTAGE IC AIRTITE NEW CONSTRUCTION HOUSING 35W MAX GU-10
R3-G19RAT	3" LINE VOLTAGE NON IC AIRTITE REMODEL HOUSING 50W MAX GU-10