

Symphony Low Voltage MiniTrack

Transformers and Dimming Controls

Specifications/Features


The Symphony system can utilize both magnetic and electronic transformers. Transformers are available for surface or remote mounting to suit installation needs.

Surface mount transformers are available in the following finishes: B (Black), P (White), S (Silver).

The electronic transformers offer the following features:


- Auto-reset electronic short circuit protection
- Auto-reset electronic overload protection
- Auto-reset thermal cut-off at 125° C
- The transformer will not work without a load
- 4 year warranty
- cULus Listed transformers

Surface Mount Transformers




Surface Mount Mono-Point Canopy
Electronic transformer, covers a standard octagon junction box. Min. load: 20W

MLA-1816-(B, P, S) - 120/12V
50W Circuit
MLA-1816-(B, P, S) 277V - 277/12V
50W Circuit
MLA-1816LED-(B, P, S) - 120/12V
2.5W - 50W



Surface Mount Feed Canopy
Electronic transformer, covers a standard square junction box, single or dual 180 degree feed. Min. load: 50W


MLA-415-(B, P, S) - 120/12V 125W



Plug-in Electronic Transformer
120/12V 60W Circuit. 10' 2-Wire cord.
Min. load: 10W


MLA-60-(B, P, S)

150W Circuit Remote Transformers



Magnetic Transformer
Magnetic circuit breaker. Black finish.


LVT-150 - (1) 120/12V 150W Circuit



Remote Electronic Transformer
Transformer must be within 12' of power stem. Black finish.

LVT-151 - (1) 120/12V
150W Circuit
LVT-151 24V - (1) 120/24V
150W Circuit

175W Remote Transformers



Electronic Transformer
(1) 120/12V 180W Circuit. (3) separate
60W output circuits, transformer must be
within 79" of power stem. Black finish.


LRT-181

Continued on Page 2

Symphony Low Voltage MiniTrack

Transformers and Dimming Controls

300W Remote Transformers




Remote Magnetic Transformer
Magnetic circuit breaker. Black finish.



LVT-300 - (1) 120/12V 300W Circuit
LVT-300-24 - (1) 120/24V 300W Circuit
LVT-300 277V - (1) 277/12V 300W Circuit


600W Remote Transformers



Remote Magnetic Transformer
Magnetic circuit breaker. Black finish.




LVT-600-24 - (1) 120/24V
600W Circuit
LVT-600-277V-24 - (1) 277/24V
600W Circuit



Remote Magnetic Transformer
(2) 120/12V 300W Circuit remote magnetic transformers, (2) magnetic circuit breakers, (1) primary. Black finish.




LVT-600-C




Remote Magnetic Transformer
(2) Remote magnetic transformers, (2) magnetic circuit breakers, (1) primary. Black finish.



LVT-500-C - (2) 120/12V 250W Circuit




Remote Magnetic Transformer
(2) 120/24V 600W Circuit remote magnetic transformers, (2) magnetic circuit breakers, (1) primary. Black finish.



LVT-1200-C-24

Dimming Controls



Dimming Controls for Magnetic Transformers
Wall plate not supplied. White finish.



LVD-600M - 600VA, 450W Max.
LVD-600M/3 - 3-Way Dimming control.
600VA, 450W Max.

Dimming Controls for Electronic Transformers
Wall plate not supplied. White finish.



LVD-300E - 300W Max.
LVD-300E/3 - 3-Way Dimming Control. 300W Max. Use with electronic transformer with switching from two locations.