





















DIMMERS

KEY  Filled-No Dimming  Empty-Dims to No Light

PRODUCT	POWER SUPPLY	Lutron Diva	Lutron Skylark	Lutron Maestro	Radio Ra2			
<p>Soraa Vivid 2 9.8W Lamp</p> 	<p>LTF Electronic Transformer p/n: TE-15L-12</p>  <p>in: 120V 50/60Hz out: 12VDC 15W MAX 5A</p>	 <p>ELECTRONIC MODEL p/n: DVELV-300P Single-Pole preset dimmer Electronic low voltage 120v-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: SELV-300P Single-Pole Preset Dimmer Electronic Low Voltage 120V-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: MAELV-600 Multi-Location Dimmer Electronic Low Voltage 120V-60Hz 600W</p>	 <p>ELECTRONIC MODELS p/n: ZP260QEW Quiet Electronic (QE) slide dimmer, Multi-Location Control 260W 120VAC 60Hz</p>			
<p>Soraa Vivid 2 10.4W Lamp</p> 	<p>LTF Electronic Transformer p/n: TE-15L-12</p>  <p>in: 120V 50/60Hz out: 12VDC 15W MAX 5A</p>	<p>0/100 dims to 6% of full light output 50 FLICKER @ 14% OUTPUT</p>	<p>0/100 dims to 6% of full light output 50 FLICKER @ 17% OUTPUT</p>	<p>0/100 dims to 8% of full light output 50 FLICKER @ 21% OUTPUT</p>	<p>0/100 dims to 0% of full light output 50 FLICKER @ 17% OUTPUT</p>			
<p>Soraa Vivid 2 11.5W Lamp</p> 	<p>LTF Electronic Transformer p/n: TE-15L-12</p>  <p>in: 120V 50/60Hz out: 12VDC 15W MAX 5A</p>	<p>0/100 dims to 5% of full light output 50 FLICKER @ 15% OUTPUT</p>	<p>0/100 dims to 5% of full light output 50 FLICKER @ 18% OUTPUT</p>	<p>0/100 dims to 7% of full light output 50 FLICKER @ 25% OUTPUT</p>	<p>0/100 dims to 0% of full light output 50 FLICKER @ 17% OUTPUT</p>			









DIMMERS

KEY  Filled-No Dimming  Empty-Dims to No Light

PRODUCT	POWER SUPPLY	Lutron Diva	Lutron Skylark	Lutron Maestro	Radio Ra2			
<p>Soraa Vivid 2 9.8W Lamp</p> 	<p>Eaglerise 75W Magnetic Transformer p/n: HLBBC-0075-003</p>  <p>in: 120V 60Hz out: 12VDC 75W MAX 6.25A</p>	 <p>ELECTRONIC MODEL p/n: DVELV-300P Single-Pole preset dimmer Electronic low voltage 120v-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: SELV-300P Single-Pole Preset Dimmer Electronic Low Voltage 120V-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: MAELV-600 Multi-Location Dimmer Electronic Low Voltage 120V-60Hz 600W</p>	 <p>ELECTRONIC MODELS p/n: ZP260QEW Quiet Electronic (QE) slide dimmer, Multi-Location Control 260W 120VAC 60Hz</p>			
<p>Soraa Vivid 2 10.4W Lamp</p> 	<p>Eaglerise 75W Magnetic Transformer p/n: HLBBC-0075-003</p>  <p>in: 120V 60Hz out: 12VDC 75W MAX 6.25A</p>	<p>0/100 dims to 20% of full light output 25 75 50</p>	<p>0/100 dims to 16% of full light output 25 75 50 FLICKER @ 21% OUTPUT</p>	<p>0/100 dims to 15% of full light output 25 75 50</p>	<p>0/100 dims to 10% of full light output 25 75 50</p>			
<p>Soraa Vivid 2 11.5W Lamp</p> 	<p>Eaglerise 75W Magnetic Transformer p/n: HLBBC-0075-003</p>  <p>in: 120V 60Hz out: 12VDC 75W MAX 6.25A</p>	<p>0/100 dims to 20% of full light output 25 75 50</p>	<p>0/100 dims to 15% of full light output 25 75 50 FLICKER @ 18% OUTPUT</p>	<p>0/100 dims to 11% of full light output 25 75 50</p>	<p>0/100 dims to 9% of full light output 25 75 50</p>			







DIMMERS

KEY  Filled-No Dimming  Empty-Dims to No Light

PRODUCT	POWER SUPPLY	Lutron Diva	Lutron Skylark	Lutron Maestro	Radio Ra2			
<p>Green Creative Titanium CRI^{SP} 7.5W</p> 	<p>LTF Electronic Transformer p/n: TE-15L-12</p>  <p>in: 120V 50/60Hz out: 12VDC 15W MAX 5A</p>	 <p>ELECTRONIC MODEL p/n: DVELV-300P Single-Pole preset dimmer Electronic low voltage 120v-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: SELV-300P Single-Pole Preset Dimmer Electronic Low Voltage 120V-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: MAELV-600 Multi-Location Dimmer Electronic Low Voltage 120V-60Hz 600W</p>	 <p>ELECTRONIC MODELS p/n: ZP260QEW Quiet Electronic (QE) slide dimmer, Multi-Location Control 260W 120VAC 60Hz</p>			
<p>Green Creative Titanium CRI^{SP} 7.7W</p> 	<p>LTF Electronic Transformer p/n: TE-15L-12</p>  <p>in: 120V 50/60Hz out: 12VDC 15W MAX 5A</p>	<p>0/100 dims to 9% of full light output 50 FLICKER @ 6% OUTPUT</p>	<p>0/100 dims to 8% of full light output 50</p>	<p>0/100 dims to 23% of full light output 50</p>	<p>0/100 dims to 1% of full light output 50 FLICKER @ 5% OUTPUT</p>			
		<p>0/100 dims to 5% of full light output 50 FLICKER @ 6% OUTPUT</p>	<p>0/100 dims to 7% of full light output 50</p>	<p>0/100 dims to 23% of full light output 50</p>	<p>0/100 dims to 5% of full light output 50 FLICKER @ 6% OUTPUT</p>			

DIMMERS

KEY  Filled-No Dimming  Empty-Dims to No Light

PRODUCT	POWER SUPPLY	Lutron Diva	Lutron Skylark	Lutron Maestro	Radio Ra2							
<p>TCP 7W Lamp MR16 GU5.3</p> 	<p>LTF Electronic Transformer p/n: TE-15L-12</p>  <p>in: 120V 50/60Hz out: 12VDC 15W MAX 5A</p>	 <p>ELECTRONIC MODEL p/n: DVELV-300P Single-Pole preset dimmer Electronic low voltage 120v-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: SELV-300P Single-Pole Preset Dimmer Electronic Low Voltage 120V-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: MAELV-600 Multi-Location Dimmer Electronic Low Voltage 120V-60Hz 600W</p>	 <p>ELECTRONIC MODELS p/n: ZP260QEW Quiet Electronic (QE) slide dimmer, Multi-Location Control 260W 120VAC 60Hz</p>	<p>0/100 dims to 3% of full light output</p> <p>25 75</p> <p>50 FLICKER @ 4% OUTPUT</p>	<p>0/100 dims to 47% of full light output</p> <p>25 75</p> <p>50</p>	<p>0/100 dims to 15% of full light output</p> <p>25 75</p> <p>50</p>	<p>0/100 dims to 1% of full light output</p> <p>25 75</p> <p>50 FLICKER @ 5% OUTPUT</p>			