

BULBRITE
LED Retrofit Lamps
Dimmer Compatibility List



PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

4W LED FILAMENT B11
Model: LED4B11/27K/FIL/D

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer	
					Min	Max*
Incandescent/Halogen	Leviton	IllumaTech	IPI06	Limited	1	6
		SureSlide	6633-P	Limited	1	6
		Vizia	VPI06-1LZ	Not Compatible	1	6
	Lutron	Toggler	TG-600	Limited	1	6
		Diva	DV-600	Limited	1	6
		Skylark	S-600	Limited	1	6
	Legrand	Maestro	MAW-600	Not Compatible	1	6
		Titan	CD703-PW	Limited	1	6
		Harmony	D703-PTC	Limited	1	6
CFL/LED Dimmers	Leviton	IllumaTech	IPL06	Limited	1	6
	Lutron	Diva	DVCL-153PL	Best	1	6
		Toggler	TGCL-153PH	Best	1	6
		Maestro	MACL-153MLH	Best	1	6
	Legrand	Skylark	CTCL-153	Best	1	6
		Harmony	DCL453-PTC	Best	1	6
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6
		IllumaTech	IPE04	Not Compatible	1	6
	Lutron	Skylark	SELVB-300P	Best	1	6
	Legrand	Scene Director	SCELV	Limited	1	6
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Not Compatible	1	6
		Decora	6613-P	Limited	1	6
	Legrand	Harmony	DLV703-PW	Limited	1	6
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6
		Miro Decorator	DRD4-W	Limited	1	6

*Max (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible - Major flickering observed, audible noise, no dimming range

Limited - Minimal adjustment may be required, audible noise may be present, minor flickering observed but does not affect dimming range and can be removed with slight dim adjustment

Best - No flickering, minor or no audible noise, wide dimming range (20% or less light output)

Dimming Range Adjustment for Lutron C•L dimmers

1. Turn dimmer on and **move slider down to the bottom.**
2. Turn adjustment dial **up** (clockwise) until lowest light level is achieved and light output is stable for all bulbs. **Note:** If dial stops, do not continue to turn.
3. Turn dimmer off, then back on to verify bulbs turn on.
4. If all bulbs do not turn on, turn adjustment dial down (counter-clockwise) slightly and repeat step 3.
5. Once all bulbs are dimming properly, install faceplate.

Contact Information:

Bulbrite Industries Inc.
145 W. Commercial Ave.
Moonachie, NJ 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com

©2015 Bulbrite Industries Inc.

All Rights Reserved.

www.bulbrite.com/LED