

MODEL SKU ST19 7W 800LM 2700K E26 SE-RCL06.1107-A

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
		DV-603P	OK	
		DVW-600PH-WH DV-603PH-WH	NC OK	
		DV-600PH-WH	OK OK	
		DVCL-153PH	NC NC	
	DIVA	DVCL-153P-WH	OK	
		DVWCL-153PH-WHC	OK	
		DV-600P-WH	NC	
		DVCL-253PH	NC OK	
		DVCL-153P-WH DVELV-300P-WH	OK OK	
	DIVA C*L	DVWCL-153PH-WH	OK	
	-	S-600	NC	
	SKYLARK	CTCL-153P-WH	OK	
		S-600PR-WH	OK	
		S-603PGH-WH	NC NC	
		S-600H-WH S-10PH	NC NC	
		SCL-153P-WH	NC NC	
		S-600-IV	OK	
		S-600-AL	OK	
		S-603PH-WH	OK	
		SCL-153PH-WH	OK	
		S-603P-WH	OK	
		SELV-300P-WH SLV-600-WH	OK OK	
		SLV-600-WH SPSELV-600M	OK OK	
	-	D-600PH-DK	NC NC	
LUTRON		MAW-600	NC NC	
		MAW-600H-AL	NC	
		MACL-153M-WH	NC	
	MAESTRO	MACL-153MR-WH	NC	
		MACL-153MH-WH	NC NC	
		MSCL-OP153MH-WH TG-603PGH-WH	NC NC	
		MAELV-600-WH	NC OK	
	-	DV-603PR	OK	
	_	D-600RH-DK	NC	
		TG-600PH-WH	OK	
	TOGGLER	TG-600PH-IV	NC	
		TGCL-153PH-WH	OK	
	-	D-600R-WH	OK	
	-	D-600R-IV DVCL-153P-WH-3	NC OK	
	-	AYCL-153P-WH	OK OK	
	ARIADNI	AY-600PH-WH	NC NC	
		AYCL-153PH	OK	
	-	CT-103P-WH	OK	
	-	S-600P-WH	OK	
	-	TG-600PNLH-WH	OK	
	-	LECL-153PH-WH	OK	
	VIVE	MACL-153MLRHW-WH MRF2S-6CL-WH	OK OK	
	CASETA	PD-6WCL-WH	OK OK	
		NTELV-300-WH	OK	
	NOVA T	NTLV-600-277-WH	OK	
	RADIO RA2	RRD-6CL-WH	OK	
LEVITON	-	6684	NC NC	
	-	NO.6683	NC OK	
	-	6631-LA IPI06	OK NC	
	-	S-600P-WH	OK	
	-	NO.6672	OK	
	-	603-6631-A	OK	
	-	6631-A	OK	
	-	NO.IPL06	NC NC	
	-	IPI10-1LZ	NC NC	
	-	6683-10Z IPI06-1LZ	NC OK	
	-	NO.6631	OK OK	
	-	6681	NC NC	
	DECORA	R62-6674-P0W	OK	
GE	-	18024	OK	
ALMOND	-	LUXDM600 - 12	OK	
AH	-	SDM3/1000	OK	
	-	SDM/600 HCL453PTC	NC NC	
LEGRAND	-	DAL06P-C2-K	NC NC	
	-	TAL06P-C2-K	NC NC	
COOPER	F	SAL06P-W-K	NC NC	
	-	AAL06-C1	NC	
MAXXIMA	=	MEW-DM600	OK	
CTL	F	DM600-12-3/LED/WH	OK	
OIL.	-	DM600-12-3	OK	
ADORNE	-	ADPD453LW2	OK OK	
	+ -	ADWR703HW4 TAL0691_C5	OK OK	
EATON	-	TAL06P1-C5	OK	

DIMMER COMPATIBILITY

DIMINIER COMI ATIBLETT				
OK	Dims to < 15%			
OK	Dims to 15 - 30%			
NC	Not Compatible			

90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
 2) The results may be different for each application depending on the installation conditions.
 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
 For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.



