90+LIGHTING

A15 6W 450LM 2700K E26



| | SE-350.045 | | |
|--------------|------------|---------------------------|---------------------|
| | | COMPATIBILITY LIST | |
| | BRAND | DIMMER MODEL | |
| MANUFACTURER | BRAND | DIMMER MODEL DVCL-153P | COMPATIBILITY OK |
| | DIVA | DVEL-ISSF DVELV-300P | <u> </u> |
| | | DVELV-303P-AL | <u> </u> |
| | | DVELC-303P-WH | <u> </u> |
| | | DV-600P-WH | OK |
| | | DVELV-300P-WH | OK |
| | | 603P-WH | OK |
| | | DVWCL-153PH | OK |
| | DIVA C*L | DVWCL-153PH-WH | ОК |
| | MAESTRO | MAELV-600 | OK |
| | | MACL-153M-WH | OK |
| | | MAELV-600-WH | ОК |
| | SKYLARK | SELV-300P | OK |
| | | CTELV-303P | OK |
| | | S-600P | OK |
| | | CTCL-153P | OK |
| | | S-603P-WH | OK |
| | | SLV-600P | OK |
| | | SCL-153P-WH | NC |
| | | S-600P-WH | OK |
| LUTRON | | SELV-300P-WH | NC |
| | | SLV-600-WH | NC |
| | LUMEA | LGCL-153P | OK |
| | | LGCL-153PL | OK |
| | | LGCL-153PLH-WH | OK |
| | VIERTI | VTELV-600M NTLV-600-WH | <u> </u> |
| | NOVA | NTLV-600-WH/jsb1-88 | OK |
| | NOVA T | NTELV-300-WH | NC |
| | | NTLV-600-277-WH | OK |
| | | RRD-6NA | OK |
| | RADIO RA2 | RRD-6CL-WH | OK |
| | VIVIE | MRF2S-6CL-WH | OK |
| | CASETA | PD-6WCL-WH | OK |
| | SPACER | SPSELV-600M | NC |
| | ARIADNI | AYCL-153P-WH | OK |
| | - | 1B3211 | OK |
| | - | 1C13I1 | OK |
| | - | VTELV-600M | OK |
| | - | DVWCL-153PH/jsb1-85 | OK |
| | - | MRF2-3LDH | OK |
| LEVITON | DECORA | R62-6674-P0W | ОК |
| | - | 6674 | ОК |
| | - | 6161 | OK |
| | - | IPI06 | OK |
| | - | 1PL06 | OK |
| | | V47-C06579 | OK |
| | - | RTD01-10Z | OK |
| | - | 6633-P | OK |
| | - | 52136 | OK |
| | - | RPI06-1/jsb1-103 | OK |
| | - | 1PL06/jsb-92 | OK |
| | - | RTD01-10Z/jsb-100 | OK |
| | - | DMB01/6 | OK |
| | - | | OK |
| FEIT | - | LGCL-153PLH-WH | OK OK |
| | | LUTRO-S-600P-WH | |
| | - | LEVITON-C20-06681-12A | OK |

DIMMER COMPATIBILITY

MODEL

| o < 15% |
|------------|
| o 15 - 30% |
| mpatible |
| · · |

90+ LIGHTING NOTES

1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.

2) The results may be different for each application depending on the installation conditions.

3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.

