



# MR16 7W DIM.

## MODEL

Model: 7MR16DIM/xxx/FL35

Where xxx means 824-965 which indicates CRI and color temperature



## MAGNETIC DIMMER SWITCH COMPATIBILITY

Brand	Series	Model	Load (w)	Cooper						Elco						Hatch						Juno						Halo											
				TF-149911-TP120						TF-149911-TP						SSH-6626002						DL1250B-H						VF180-210						QE001292AS					
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6
Lutron	Abella	ABLV-1000M	1000	OK*						OK*						OK						OK*						OK						OK*					
	Skylark	SLV-600P	600	OK						OK						OK						OK						OK						OK					
	Maestro	MALV-600	600	OK*						OK*						OK						OK*						OK*						OK*					
Legrand	Harmony	H703PTU	600	OK*						OK*						OK*						OK						OK*						OK*					
	Adorne	ADTP703TU	700	OK						OK						OK						OK						OK						OK					
Leviton	Sure Slide	6613-P	600	OK						OK						OK*						OK						OK						OK					
	VIZA+	VPM10	1000	OK*						OK*						OK						OK						OK*						OK*					
Cooper	Devine	DAL06P	300	OK						OK						OK*						OK						OK						OK					
	Aspire	9536	600	OK*						OK*						OK*						OK						OK*						OK*					

\*Minimum 2 lamps  
OK- Fully Compatible  
X - Not Compatible

## ELECTRONIC DIMMER SWITCH COMPATIBILITY

Brand	Series	Model	Load (w)	Hatch																																			
				RS12-60M-LED (DC1340)						RS12-80M (DC1412)						RS12-60M (DC1124LED)						RS12-60M (DC1130)						RS12-30M-LED (DC1413)						RS12-15M-LED (DC1513K)					
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6						
Lutron	Maestro	MAELV-600	600	OK						OK						OK						OK						OK						OK					
	Contour	CTELV-303P	300	OK						OK						OK						OK						OK						OK					
	Diva	DVELV-300P	300	OK						OK						OK						OK						OK						OK					
	Nova	NTELV-600	600	OK						OK						OK						OK						OK						OK					
Leviton	IllumaTech	IPE04-1LZ	300	X						X						X						X						X						OK*					

\*Minimum 3 lamps  
OK- Fully Compatible  
X - Not Compatible

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



# MR16 7W DIM.

## ELECTRONIC TRANSFORMER COMPATIBILITY

Brand	Model	Dimmability
Hatch	RS12-15M-LED	OK
	RS12-30M-LED	OK
	RS12-60M-LED	OK
	RS12-60M	OK
	RS12-80M	X
	RS12-80MGN	OK
	RS24-80M	X
	RS12-80BFS	OK
	RS12-60BF-LED	OK
	RL12-60A	OK
	RS12-80-277M	OK
	RS12-80BF-277	OK
	RL12-75A-277	X
Lichtech	LET60	OK
	LET75	OK
	LET151R	OK

## MAGNETIC TRANSFORMER COMPATIBILITY

Brand	Model	Dimmability
Lichtech	SSH-6626002	OK
Cooper	CH50	OK
Juno	VF180-210	OK
Nora	TJ-H-277-80-1	OK

OK- Fully Compatible

X - Not Compatible

GREEN CREATIVE has provided this transformer compatibility chart for guidance when selecting a transformer and lamp combination. Our lamps were tested for compatibility with the above listed transformers. Transformers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above transformers may affect performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.