



DIMMER COMPATIBILITY

Project: _____

Fixture Type: _____

Location: _____

Contact/Phone: _____

Incandescent and Magnetic Low Voltage - Forward Phase Dimming

- Dimmable with the use of most forward phase dimmers • Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W
 Dimmer Rating = 600W
 Equivalent Incandescent Load (EIL) Factor = 50% (.5)
 $(600/10) \times .5 = 30$ Fixtures per Dimmer

Electronic Low Voltage - Reverse Phase Dimming

- Dimmable with the use of most electronic low voltage dimmers • Electronic low voltage dimmers require a neutral wire in the wall box • Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W
 Dimmer Rating = 600W
 Equivalent Incandescent Load (EIL) Factor = 75% (.75)
 $(600/10) \times .75 = 45$ Fixtures per Dimmer

Juno Qualified Dimmers

Fixture Series	Lutron® Model Numbers:	Leviton® Model Numbers:	Lutron® Model Numbers:	Leviton® Model Numbers:
JUNO BASICS SERIES™ LED RETROFIT TRIM, GEN2 4RLD, 5RLD and 6RLD Series	Ariadn® AYCL Series Diva® DVCL Series Diva® DVLV Series* Glyder® GLV Series* Lutron® Homeworks® RPM-4U* Lutron® Homeworks® QS HQRD-10ND Series* Lutron® Homeworks® QS HQRD-6ND Series* Lutron® Radio RA2® RRD-10ND Series* Maestro® MACL Series† Maestro® WIRELESS MRF2-6ND Series* Nova T® NT Series Skylark® Contour CTCL Series Skylark® SCL Series Skylark® SLV Series	Sureslide 6633*	Diva® DVELV Series* Lutron® Grafik Eye PHPM-PA Series Lutron® Homeworks® QS HQRD-6NA Series* Lutron® Radio RA2® RRD-6NA Series* Maestro® MAELV Series* Maestro® MRF2-6ELV Series* Nova T® NTELV Series* Skylark® SELV Series*	
600 LUMEN JUNO BASICS SERIES™ LED ADJUSTABLE RETROFIT TRIM 4RLA, 5RLA and 6RLA Series	Diva® DVLV Series* Glyder® GLV Series* Lutron® Homeworks® RPM-4U* Lutron® Homeworks® QS HQRD-10ND Series* Lutron® Homeworks® QS HQRD-6ND Series* Lutron® Radio RA2® RRD-10ND Series* Maestro® WIRELESS MRF2-6ND Series* Nova T® NT Series Skylark® SLV Series	Sureslide 6633*	Diva® DVELV Series* Lutron® Grafik Eye PHPM-PA Series Lutron® Homeworks® QS HQRD-6NA Series* Lutron® Radio RA2® RRD-6NA Series* Maestro® MAELV Series* Maestro® MRF2-6ELV Series* Nova T® NTELV Series* Skylark® SELV Series*	
900 LUMEN JUNO BASICS SERIES™ COMMERCIAL LED RETROFIT TRIM 6RLC Series	Ceana® CNLV Diva® DVLV Series* Glyder® GLV Series* Lutron® Homeworks® QS HQRD-10ND Series Lutron® Homeworks® QS HQRD-6ND Series Lutron® Radio RA2® RRD-10ND Series Lutron® Radio RA2® RRD-6NA Maestro® WIRELESS MRF2-6ND Series Nova T® NTLV Series	Sureslide 6633*	Diva® DVELV Series* Faedra® FAELV Series Lutron® Homeworks® QS HQRD-6NA Series Lutron® Radio RA2® RRD-6NA Series Maestro® MAELV Series* Maestro® MRF2-6ELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series	

*Juno recommended dimmers †Minimum 3 fixtures required for best performance *Minimum load required; see dimmer manufacturer for requirement
 Consult technical services for additional information regarding other dimmer model qualification.



DIMMER COMPATIBILITY

Project: _____

Fixture Type: _____

Location: _____

Contact/Phone: _____

Incandescent and Magnetic Low Voltage - Forward Phase Dimming

- Dimmable with the use of most forward phase dimmers
- Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W
 Dimmer Rating = 600W
 Equivalent Incandescent Load (EIL) Factor = 50% (.5)
 $(600/10) \times .5 = 30$ Fixtures per Dimmer

Electronic Low Voltage - Reverse Phase Dimming

- Dimmable with the use of most electronic low voltage dimmers
- Electronic low voltage dimmers require a neutral wire in the wall box
- Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W
 Dimmer Rating = 600W
 Equivalent Incandescent Load (EIL) Factor = 75% (.75)
 $(600/10) \times .75 = 45$ Fixtures per Dimmer

Juno Qualified Dimmers

Fixture Series	Lutron® Model Numbers:	Leviton® Model Numbers:	Lutron® Model Numbers:	Leviton® Model Numbers:
700 and 1000 LUMEN JUNO BASICS SERIES™ SURFACE MOUNT FIXTURE 4RLS and 6RLS Series	Ariadni® AYCL Series* Diva® DVCL Series* Diva® DVLV Series* Diva® DV Series Glyder® GLV Series* Lutron® Homeworks® RPM-4U* Lutron® Homeworks® RPM-4A Lutron® Radio RA2® RRD-6D Series* Lutron® Radio RA2® RRD-10ND Series* Nova T® NT Series* Nova T® NTLV-600 Series Rotary D Series* Skylark® Contour CTCL Series* Skylark® SCL Series* Skylark® SLV Series*	IllumaTech™ IPL06 Series Sureslide 6613* Sureslide 6633*	Diva® DVELV Series* Lutron® Grafik Eye QS-3P and 6P Series Lutron® Radio RA2® RRD-6NA Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series*	IllumaTech™ IPE04* Vizia VPE06-1LX

* Juno recommended dimmers † Minimum 3 fixtures required for best performance * Minimum load required; see dimmer manufacturer for requirement
 Consult technical services for additional information regarding other dimmer model qualification.