

# Lightology

lightology.com  
866-954-4489  
10-10-25

Project: \_\_\_\_\_  
Company: \_\_\_\_\_  
Location: \_\_\_\_\_ Fixture Type: \_\_\_\_\_  
SPEC #: **AST1377175**  
Approved On: \_\_\_\_\_ Approved By: \_\_\_\_\_

## 12W 500mA Constant Current 0-10V LED Driver - Overstock

By Astro Lighting



### Description

The 12 Watt Class 2 500mA Constant Current 0-10V LED Driver is designed for use with Astro Lighting products requiring a driver. Input Voltage: 108-305V AC. 47/63Hz. Minimum Output Voltage: 8.0V Maximum Output Voltage: 24.0V. Minimum Output Power: 4W. Maximum Output Power: 17W. Suitable for wet locations. Dimmable with 0-10V dimmers, sold separately. Note: 1 minimum / 2 maximum fixtures can be used with this driver.



Shown in black

### Specifications

|                   |                          |
|-------------------|--------------------------|
| COLOR             | N/A                      |
| BODY FINISH       | Black                    |
| WATTAGE           | 12W                      |
| DIMMER            | 0-10V                    |
| DIMENSIONS        | 3.35"W x 1.42"H x 0.91"D |
| BULB NOT INCLUDED | N/A                      |
| COUNTRY OF ORIGIN | China                    |



CLICK TO VIEW PRODUCT

Notes: