

Lightology

lightology.com
866-954-4489
04-25-26

Project: _____

Company: _____

Location: _____ Fixture Type: _____

SPEC #: **ELE342224**

Approved On: _____ Approved By: _____

300W 12V LED Remote Electronic Transformer

By Visual Comfort Architectural




Description

This 300 watt 12 volt remote LED electronic transformer converts standard 120 line voltage to 12 volts, providing the necessary voltage for powering a Monorail, Kable Lite, Wall Monorail or Freejack low voltage lighting system. Can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting short circuit and overload protection that will safely turn off the system should a short occur. Once the short is removed, the unit can be reset by simply flipping the wall switch off and back on. Transformer must be installed in a remote, but accessible location such as above the ceiling or in a closet, and should be located no more than 20 feet from the required single feed power feed, sold separately. ETL listed. 8.5 inch length x 3.5 inch width x 2 inch height.



Shown in black



Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	300W
DIMMER	Low Voltage Electronic
DIMENSIONS	8.5"L x 3.5"W x 2"H
BULB	N/A



CLICK TO VIEW PRODUCT

Notes: