
























































ELECTRONIC DIMMERS

KEY  Filled-No Dimming  Empty-Dims to No Light

PRODUCT	POWER SUPPLY	Lutron Diva	Lutron Skylark	Lutron Maestro	Lightolier Sunrise	Leviton Vizia	Lutron Nova	Additional Option
		 <p>ELECTRONIC MODEL p/n: DVELV-300P Single-Pole preset dimmer Electronic low voltage 120v-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: SELV-300P Single-Pole Preset Dimmer Electronic Low Voltage 120V-60Hz 300W</p>	 <p>ELECTRONIC MODELS p/n: MAELV-600 Multi-Location Dimmer Electronic Low Voltage 120V-60Hz 600W</p>	 <p>ELECTRONIC MODELS p/n: ZP260QEW Quiet Electronic (QE) slide dimmer, Multi-Location Control 260W 120VAC 60Hz</p>	 <p>ELECTRONIC MODELS p/n: VPE06 Electronic Low Voltage Dimming, Single Pole 600W 120VAC 60Hz</p>	 <p>ELECTRONIC MODEL p/n: NELV-450 Single-pole slide dimmer Electronic Low Voltage 120V-60Hz 450W</p>	 <p>NON-DIM ONLY p/n: RRD-8ANS 8A Lighting 1/4 HP Motor Load Switch with Neutral Wire</p>
SS1- SS2P- SS2C- SS3- 	EDGE Lighting TEB-60L-12DC (electronic)  in: 120V 50/60Hz out: 12VDC 60W MAX 5A	 <p>0/100 dims to 8% of full light output</p>	 <p>0/100 dims to 10% of full light output</p>	 <p>0/100 dims to 16% of full light output</p>	 <p>0/100 dims to 7% of full light output</p>	 <p>0/100 dims to 69% of full light output</p>	 <p>0/100 dims to 7% of full light output</p>	
SS1- SS2P- SS2C- SS3- 	EDGE Lighting PSB-60W-ELV-12VDC w/potentiometer (electronic)  in: 120/240VAC 50/60Hz out: 12VDC 60W MAX 5A	 <p>0/100 dims to 26% of full light output</p>	 <p>0/100 dims to 26% of full light output</p>	 <p>0/100 dims to 26% of full light output</p>	N/A	N/A	N/A	
SS1- SS2P- SS2C- SS3- 	EDGE Lighting TEB-60L-24DC (electronic)  in: 120V 50/60Hz out: 24VDC 60W MAX 2.5A	 <p>0/100 dims to 20% of full light output</p>	 <p>0/100 dims to 17% of full light output</p>	 <p>0/100 dims to 15% of full light output</p>	N/A	N/A	 <p>0/100 dims to 14% of full light output</p>	

0-10 VOLT DIMMERS

KEY  Filled-No Dimming  Empty-Dims to No Light

PRODUCT	POWER SUPPLY	Lutron Radio RA2 W/ GRX-TVI	Lutron Grafik Eye QS W/ GRX-TVI	Lightolier Sunrise	Lutron NOVA T	Lutron DIVA	Leviton IP710-DLX	
		 Lutron Radio RA2 p/n: RRD-10ND 120VAC, 60Hz 1000W USED WITH  Lutron Grafik Eye p/n: GRX-TVI 20VAC, 60Hz 1000W	 Lutron Grafik Eye QS p/n: QSGRJ-XP 120VAC, 60Hz 1000W USED WITH  Lutron Grafik Eye p/n: GRX-TVI 120VAC, 60Hz 1000W	 ELECTRONIC MODEL p/n: ZP600FAM120 0-10VDC dimmable electronic preset dimmer 600VA, 120VAC, 60Hz	 ELECTRONIC MODEL p/n: NTFTV-WH 0-10VDC dimmable electronic preset dimmer 120VAC 60Hz USED WITH  Lutron Grafik Eye p/n: PP20 120VAC, 60Hz	 ELECTRONIC MODEL p/n: DVTV 0-10VDC dimmable electronic preset dimmer 120VAC 60Hz USED WITH  Lutron Grafik Eye p/n: PP20 120VAC, 60Hz	 ELECTRONIC MODEL p/n: IP710-DLX 0-10VDC dimmable electronic preset dimmer 1200VA, 120VAC, 60Hz	
SS1- SS2P- SS2C- SS3- 	EDGE Lighting PSB-96W-010-24VDC  in: 120V 50/60Hz out: 24VDC 96W MAX 4A	0/100 dims to  7% of full light output	0/100 dims to  7% of full light output	0/100 dims to  7% of full light output	0/100 dims to  7% of full light output	0/100 dims to  13% of full light output	0/100 dims to  7% of full light output	
SS1- SS2P- SS2C- SS3- 	EDGE Lighting PSB-2X96W-010-24VDC  in: 120V 50/60Hz out: 24VDC 2x96W MAX 2x4A	0/100 dims to  7% of full light output	0/100 dims to  7% of full light output	0/100 dims to  7% of full light output	0/100 dims to  7% of full light output	0/100 dims to  13% of full light output	0/100 dims to  7% of full light output	