














1718 W. Fullerton Ave
Chicago, IL 60614
Tel: 773-770-1195
Fax: 773-935-5613
www.edgelighting.com
info@edgelighting.com










MAGNETIC DIMMERS

KEY Filled-No Dimming Empty-Dims to No Light

		LUTRON DIVA	LUTRON SKYLARK	LUTRON MAESTRO	LIGHTOLIER SUNRISE	LUTRON RADIO RA2	
PRODUCT	POWER SUPPLY	 <p>MAGNETIC MODEL p/n: DVLV-600P Single-Pole present dimmer Magnetic low voltage 120V-60Hz 300W</p>	 <p>MAGNETIC MODEL p/n: SLV-600P Single-Pole Preset Dimmer Magnetic Low Voltage 120V-60Hz 300W</p>	 <p>MAGNETIC MODEL p/n: MALV-600 Multi-Location Dimmer Magnetic Low Voltage 120V-60Hz 600W</p>	 <p>MAGNETIC MODEL p/n: ZP600VA Magnetic Low Voltage 120V-60Hz 600W</p>	 <p>MAGNETIC MODEL p/n: RRD-6NA Multi-Location Dimmer Magnetic Low Voltage 120V-60Hz 600W</p>	
<p>SUN3</p> 	<p>EDGE LIGHTING T-150-12</p>  <p>in: 120VAC 50/60Hz out: 12VAC 150W MAX 12.5A</p>	<p>0/100 dims to 16% of full light output</p> 	<p>0/100 dims to 39% of full light output</p> 	N/A	<p>0/100 dims to 59% of full light output</p> 	<p>0/100 dims to 4% of full light output</p> 	

ELECTRONIC DIMMERS

KEY Filled-No Dimming Empty-Dims to No Light

		LUTRON DIVA	LUTRON SKYLARK	LUTRON MAESTRO	LIGHTOLIER SUNRISE	
PRODUCT	POWER SUPPLY	 <p>ELECTRONIC MODEL p/n: DVELV-300P Single-Pole present dimmer Electronic low voltage 120V-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: SELV-300P Single-Pole Preset Dimmer Electronic Low Voltage 120V-60Hz 300W</p>	 <p>ELECTRONIC MODEL p/n: MAELV-600 Multi-Location Dimmer Electronic Low Voltage 120V-60Hz 600W</p>	 <p>ELECTRONIC MODEL p/n: ZP260QE Quiet Electronic (QE) Slide Dimmer Multi-Location Dimmer 260W 120VAC 60Hz</p>	
<p>SUN3</p> 	<p>EDGE LIGHTING TE-60L-12</p>  <p>in: 120VAC 50/60Hz out: 11.5 VAC 60W MAX 5A</p>	<p>0/100 dims to 9% of full light output</p> 	<p>0/100 dims to 21% of full light output</p> 	<p>0/100 dims to 31% of full light output</p> 	TBD	