



1. Shut off the main electrical supply from the main fuse box/circuit breaker.

- 2. Attach mounting plate to wall or junction box using mounting screws (C).
- 3. Connect ground wire from wall to ground wire from lamp using wire caps (A).
- 4. Attach house wire to lamp wires as shown. Fasten the pairs together with a wire caps.

DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OR SAFETY WILL BE

- 5. Attach front face of light to back plate by inserting canopy screws (B) through predrilled holes in front face and into back plate as shown. Tighten using
- 7. Restore power to junction box and test fixture.

DO NOT EXCEED SPECIFIED MAX WATTAGE.

