

Titanium Series 4.0 MR16 6W 6MR16G4DIM



Magnetic Dimmer Switch Compatibility

	Series	Model		Dimmability (# of lamps)																							
Brand			Load	HALC	ELCO CAN				NORA CAN		JUNO CAN		ELG transf.					ESBCO transf.									
				1	2	1	2	3	4	5	1	2	3	1	2	1	2	3	4	5	6	1	2	3	4	5	6
LUTRON	Abella	ABLV-1000M	1000	20%-100%			OK		-	Х		20%-100%		15%-100%)%	OK		Х								
	Maestro	MALV-1000	1000	Х		Х	X)K	K		Х		Х		Х			OK			X					
	Nova	NTELV-600	600	20%-100%		Х		OK		Х		OK		OK				OK				Х					
	Skylark	S-600	600	15%-100%		Х		OK			Х		30%-100%		OK			OK									
	Skylark	SLV-600P	600	15%-100%		20%-10		0%-100%		Х		25%-90%		15%-100%			Х										
LEVITON	Sure Slide	6613-P	600	10%-100%		10%-100			0%		Х		ОК		OK				Х								
	VIZA+	VPM10	1000		Х			10%-100%			Х		OK		ХОК			X									
COOPER	Aspire	9539	600	20%-	·100%		15%-100%)0%		Х		(ЭК	OK				X			OK	1				

Table Key

OK= Fully compatible

-% = Compatible within this range

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.

10			E		ım Series 4.0 MF 6MR16G4DIM nmer Switc h	R16 6W	ty	GR) Eativ	√E			
Brand	Series	Model	Load		Hatch	s)) Lightech							
				RS 12-80M 1 2 3 4 5 6	RS 12-60M(LED) 1 2 3 4 5 6	RS 12-60M 1 2 3 4 5 6	LRT75 1 2 3 4		LF 1 2 3	RT60 4 5	6			
LUTRON	Skylark	SELV-300P	600		OK				OK					
LEVITON	Sure Slide	6613-P0W	1000		OK		ОК							
		6615-P0W	1000		Х				Х					
	, compatible	e within this ra	ange]									

A110

*GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.