



# DIMMER COMPATIBILITY

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

		DEDICATED 120V ONLY HOUSING				UNIVERSAL VOLTAGE			
		<p><b>Incandescent and Magnetic Low Voltage - Forward Phase Dimming</b></p> <ul style="list-style-type: none"> <li>Dimmable with the use of most forward phase dimmers</li> <li>Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.</li> </ul> <p>Example: Fixture Rating = 10W                      Dimmer Rating = 600W                      Equivalent Incandescent Load (EIL) Factor = 50% (.5)                      (600/10) X .5 = 30 Fixtures per Dimmer</p>		<p><b>Electronic Low Voltage - Reverse Phase Dimming</b></p> <ul style="list-style-type: none"> <li>Dimmable with the use of most electronic low voltage dimmers</li> <li>Electronic low voltage dimmers require a neutral wire in the wall box</li> <li>Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.</li> </ul> <p>Example: Fixture Rating = 10W                      Dimmer Rating = 600W                      Equivalent Incandescent Load (EIL) Factor = 75% (.75)                      (600/10) X .75 = 45 Fixtures per Dimmer</p>		<p><b>Universal Voltage (120-277V) Housings</b></p> <p>0-10V Dimming Control</p> <ul style="list-style-type: none"> <li>Dimming range of 100% down to 10% or lower with a minimum load of one fixture.</li> </ul> <p>† Additional Lutron products required for switching functionality when using Lutron 0-10V dimmers (such as PP-20)</p> <p>Note: C-Bus is 25 fixtures per channel.</p>			
		Juno Qualified Dimmers				Juno Qualified Dimmers			
Fixture Series		Lutron® Model Numbers:	Leviton® Model Numbers:	Whole House Integrated Control Systems:	Lutron® Model Numbers:	Leviton® Model Numbers:	Lutron® Model Numbers:	Leviton® Model Numbers:	Whole House Integrated Control Systems:
600 LUMEN LED DOWNLIGHT AND RETROFIT WARMDIM® IC 4", 5" and 6" Generation 4N Series		Ariadni® AY* Ceana® CNLV* Diva® DV*/DVLV* Series Glyder® GLV Series* Nova T® NT Series Nova T® NTLV* Rotary D* Series Skylark® S* Skylark® SLV* Series Toggle® TG*	IllumaTech™ IPL06 Series Sureslide 6613* Sureslide 6633*	Lutron® GRAFIK Eye QSGR-RP* Lutron® Homeworks® LP-RPM-4A Lutron® Homeworks® LP-RPM-4U* Lutron® Homeworks® QS HQRD-10ND Lutron® Radio RA2® RRD-10ND	Diva® DVELV Series* Faedra® FAELV* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IllumaTech™ IPE04 Vizia VPE06-1LX*			
600 LUMEN LED DOWNLIGHT AND RETROFIT WARMDIM® IC 4", 5" and 6" Generation 3 & 4 Series		Ariadni® AY*/AYCL Series Ceana® CNLV* Series Diva® DV*/DVCL*/DVLV* Series Glyder® GLV Series* Lumea® LGCL Series Nova T® NT*/NTLV* Series Rotary D Series Skylark® Contour CTCL Series Skylark® S*/SLV* Series Spacer System® SPSLV Series Toggle® TGCL Series	IllumaTech™ IPL06 Series Trimatron 6681*	Lutron® Homeworks® QS HQRD-10ND Lutron® Homeworks® QS HQRD-6NA* Lutron® Radio RA2® RRD-10ND Lutron® Radio RA2® RRD-6D Lutron® Radio RA2® RRD-6NA* Schneider Electric C-Bus SLC5504TD4A*	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IllumaTech™ IPE04*			
600 LUMEN LED DOWNLIGHT IC 4", 5" and 6" Generation 4 Series		Ariadni® AY*/AYCL* Series Ceana® CNLV* Series Diva® DV*/DVCL*/DVLV* Series Glyder® GLV Series* Lumea® LGCL* Series Nova T® NT Series Nova T® NTLV* Series Rotary D* Series Skylark® Contour CTCL* Series Skylark® S*/SLV* Series Toggle® TGCL* Series	IllumaTech™ IPL06 Series Sureslide 6613* Sureslide 6633*	Lutron® GRAFIK Eye QS PHPM-PA* Lutron® GRAFIK Eye QSGR-RP* Lutron® Homeworks® LP-RPM-4A Lutron® Homeworks® LP-RPM-4U Lutron® Homeworks® QS HQRD-6NA* Lutron® Radio RA2® RRD-10ND* Lutron® Radio RA2® RRD-6NA*	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IllumaTech™ IPE04 Series* Vizia VPE06-1LX*	Diva® DVTV Series <sup>1</sup> GRAFIK Eye QS GRX-TVI Nova T® NTFTV Series <sup>1</sup> Nova® NFTV Series <sup>1</sup>	IllumaTech™ IP710-DLX Series	Schneider Electric C-Bus SLCLE5504TAMP* Lutron® Homeworks® GRX-TVM2
600 LUMEN LED DOWNLIGHT IC 4", 5" and 6" Generation 3† Series		Ariadni® AY*/AYCL Series Ceana® CNLV Series Diva® DV*/DVCL*/DVLV Series Glyder® GLV Series Lumea® LGCL Series Nova T® NT/NTLV Series Skylark® Contour CTCL Series Skylark® S*/SLV Series Toggle® TG/TGCL Series	IllumaTech™ IPL06 Series Trimatron 6681	Lutron® Homeworks® QS HQRD-6NA Lutron® Radio RA2® RRD-10ND Lutron® Radio RA2® RRD-6NA Schneider Electric C-Bus SLC5504TD4A	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*		Diva® DVTV Series <sup>1</sup> GRAFIK Eye QS GRX-TVI Nova T® NTFTV Series <sup>1</sup> Nova® NFTV Series <sup>1</sup>	IllumaTech™ IP710-DLX Series	Schneider Electric C-Bus SLCLE5504TAMP* Lutron® Homeworks® GRX-TVM2

† J6RLG3 and J6RLEG3 series dimmers listed under dedicated 120V only housing, including incandescent, magnetic low voltage and electronic low voltage.

\* Juno recommended dimmers  
 Consult technical services for additional information regarding other dimmer model qualification.





# DIMMER COMPATIBILITY

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

		DEDICATED 120V ONLY HOUSING				UNIVERSAL VOLTAGE					
		<p>Incandescent and Magnetic Low Voltage - Forward Phase Dimming</p> <ul style="list-style-type: none"> <li>• Dimmable with the use of most forward phase dimmers</li> <li>• Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.</li> </ul> <p>Example: Fixture Rating = 10W                      Dimmer Rating = 600W                      Equivalent Incandescent Load (EIL) Factor = 50% (.5)                      (600/10) X .5 = 30 Fixtures per Dimmer</p>				<p>Electronic Low Voltage - Reverse Phase Dimming</p> <ul style="list-style-type: none"> <li>• Dimmable with the use of most electronic low voltage dimmers</li> <li>• Electronic low voltage dimmers require a neutral wire in the wall box</li> <li>• Dimming range of 100% down to 5% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.</li> </ul> <p>Example: Fixture Rating = 10W                      Dimmer Rating = 600W                      Equivalent Incandescent Load (EIL) Factor = 75% (.75)                      (600/10) X .75 = 45 Fixtures per Dimmer</p>			<p>Universal Voltage (120-277V) Housings</p> <p>0-10V Dimming Control</p> <ul style="list-style-type: none"> <li>• Dimming range of 100% down to 10% or lower with a minimum load of one fixture.</li> </ul> <p>† Additional Lutron products required for switching functionality when using Lutron 0-10V dimmers (such as PP-20)</p> <p>Note: C-Bus is 25 fixtures per channel.</p>		
		Juno Qualified Dimmers				Juno Qualified Dimmers					
Fixture Series		Lutron® Model Numbers:	Leviton® Model Numbers:	Whole House Integrated Control Systems:	Lutron® Model Numbers:	Leviton® Model Numbers:	Whole House Integrated Control Systems:				
900 LUMEN LED DOWNLIGHT WARMDIM® IC 4" Generation 4 Series		Ariadni® AY* Series Ceana® CNLV* Series Diva® DV*/DVLV* Series Glyder® GLV Series* Nova T® NTLV* Series Skylark® S*/SLV* Series	IlumaTech™ IPL06 Series* Sureslide 6613	Lutron® GRAFIK Eye PHPM-PA Lutron® GRAFIK Eye QSGR-RP Lutron® Homeworks® LP-RPM-4A Lutron® Homeworks® LP-RPM-4U Lutron® Radio RA2® RRD-6NA*	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IlumaTech™ IPE04 Vizia VPE06-1LX*					
900 LUMEN LED DOWNLIGHT WARMDIM® 5" and 6" Generation 4 Series		Ariadni® AY* Series Ceana® CNLV* Series Diva® DV*/DVLV* Series Glyder® GLV Series* Nova T® NT/NTLV* Series Rotary D Series Skylark® S*/SLV* Series Toggle® TG*	IlumaTech™ IPL06 Series Sureslide 6613* Sureslide 6633*	Lutron® GRAFIK Eye QS PHPM-PA* Lutron® GRAFIK Eye QSGR-RP* Lutron® Homeworks® LP-RPM-4A Lutron® Homeworks® LP-RPM-4U* Lutron® Homeworks® QS HQRD-10ND Lutron® Radio RA2® RRD-10ND Lutron® Radio RA2® RRD-6D	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IlumaTech™ IPE04 Vizia VPE06-1LX*					
900 LUMEN LED DOWNLIGHT IC 4" Generation 4 Series		Ariadni® AY Series* Ceana® CNLV Series* Diva® DV*/DVLV* Series Glyder® GLV Series* Nova T® NT/NTLV* Series Rotary D Series Skylark® S*/SLV* Series Toggle® TG Series*	IlumaTech™ IPL06* Series Sureslide 6613* Sureslide 6633*	Lutron® GRAFIK Eye QS PHPM-PA* Lutron® GRAFIK Eye QSGR-RP* Lutron® Homeworks® QS HQRD-6NA Lutron® Homeworks® QS HQRD-10ND Lutron® Homeworks® RPM-4A* Lutron® Homeworks® RPM-4U Lutron® Radio RA2® RRD-6NA Lutron® Radio RA2® RRD-10ND	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Maestro® MRF2-6ELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IlumaTech™ IPE04 Series* Vizia VPE06-1LX*					
900 LUMEN LED DOWNLIGHT IC 5" and 6" Generation 4 Series		Ariadni® AY*/AYCL* Series Ceana® CNLV* Series Diva® DV*/DVCL*/DVLV* Series Glyder® GLV Series* Lumea® LGCL* Series Nova T® NT Series Nova T® NTLV* Series Rotary D* Series Skylark® Contour CTCL* Series Skylark® S*/SLV* Series Toggle® TGCL* Series	IlumaTech™ IPL06 Series Sureslide 6613* Sureslide 6633*	Lutron® GRAFIK Eye QS PHPM-PA* Lutron® GRAFIK Eye QSGR-RP* Lutron® Homeworks® LP-RPM-4A Lutron® Homeworks® LP-RPM-4U Lutron® Homeworks® QS HQRD-6NA* Lutron® Radio RA2® RRD-10ND* Lutron® Radio RA2® RRD-6NA*	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IlumaTech™ IPE04 Series* Vizia VPE06-1LX*	Diva® DVT Series! GRAFIK Eye QS GRX-TVI Nova T® NTFTV Series! Nova® NFTV Series!	IlumaTech™ IP710-DLX Series Schneider Electric C-Bus SLCLE5504TAMP* Lutron® Homeworks® GRX-TVM2			
900 LUMEN LED DOWNLIGHT IC 5" and 6" Generation 3† Series		Ariadni® AY*/AYCL* Series Ceana® CNLV* Series Diva® DV*/DVCL*/DVLV* Series Glyder® GLV Series* Lumea® LGCL* Series Nova T® NTLV* Series Skylark® Contour CTCL* Series Skylark® S*/SLV* Series Toggle® TGCL* Series	IlumaTech™ IPL06 Series Trimatron 6681	Lutron® Homeworks® QS HQRD-6NA* Lutron® Radio RA2® RRD-10ND Lutron® Radio RA2® RRD-6D Lutron® Radio RA2® RRD-6NA* Schneider Electric C-Bus SLC5504TD4A*	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IlumaTech™ IPE04 Series	Diva® DVT Series! GRAFIK Eye QS GRX-TVI Nova T® NTFTV Series! Nova® NFTV Series!	IlumaTech™ IP710-DLX Series Schneider Electric C-Bus SLCLE5504TAMP* Lutron® Homeworks® GRX-TVM2			
1400 LUMEN LED DOWNLIGHT IC 5" and 6" Generation 4 Series		Ariadni® AY*/AYCL* Series Ceana® CNLV* Series Diva® DV*/DVCL*/DVLV* Series Glyder® GLV Series* Lumea® LGCL* Series Nova T® NT/NTLV* Series Rotary D Series Skylark® Contour CTCL* Series Skylark® S*/SLV* Series Toggle® TGCL* Series	IlumaTech™ IPL06 Series* Sureslide 6613-PLW* Sureslide 6633*	Lutron® GRAFIK Eye QS PHPM-PA Lutron® GRAFIK Eye QSGR-RP Lutron® Homeworks® LP-RPM-4A* Lutron® Homeworks® LP-RPM-4U Lutron® Homeworks® QS HQRD-10ND* Lutron® Homeworks® QS HQRD-6NA* Lutron® Homeworks® QS HQRD-6ND Lutron® Radio RA2® RRD-10ND* Lutron® Radio RA2® RRD-6NA* Maestro® WIRELESS MRF2-6ND	Diva® DVELV Series* Faedra® FAELV Series* Maestro® MAELV Series* Nova T® NTELV Series* Skylark® SELV Series* Spacer System® SPSELV Series*	IlumaTech™ IPE04 Series* Vizia VPE06-1LX*					

† J6RLG3 and J6RLEG3 series dimmers listed under dedicated 120V only housing, including incandescent, magnetic low voltage and electronic low voltage.

\* Juno recommended dimmers  
 Consult technical services for additional information regarding other dimmer model qualification.

