

SORAA AR111 12.5 WATT DIMMER/TRANSFORMER (MAGNETIC) COMPATIBILITY LIST - North America

Transformer	Dimmer -->		Lutron Grafik Eye E9300	Lutron Skylink SLV-600P	Lutron Diva DVLV-600P	Lutron Caseta CLVL-600P	Lutron NTLV-600	MARLIN CONTROLS Stellar DIMMING CABINET P/N 6-3-08-20-3-103T with RMS 8 Control Unit - approx. 6 Kilo-Watts Total	Lutron Radio RA2 IRD-6NA-WH-600W	Lutron Radio RA2 RRD-10D-SW-800W
North America										
Basler Electric	MI-5481E	Magnetic	10%	92%	92%	92%		9%		
Cooper	TF-149911	Magnetic	11%	NC	NC	NC		7%		
Cooper	TF 149911-TP120	Magnetic	10%	NC	NC	NC		9%		
Cooper	TFA4120	Magnetic			28%				19%	
Hammond Manufacturing	166Q12	Magnetic	13%	NC	NC	NC		10%		
Hatch	LS12-50EN	Magnetic								
Iris	TFA212	Magnetic					19%		24%	
Iris	TFA311T	Magnetic					19%		15%	
Juno	310-1333	Magnetic	13%	NC	NC	NC		10%		
Linea	701970	Magnetic	13%	NC	NC	NC		9%		
MDL Corp	315-0071A – IRIS RPN3MR Fixture dimmer Tap	Magnetic		28%	35%					
MDL Corp	315-0071A – IRIS RPN3MR Fixture Normal Tap	Magnetic		27%	33%				9%	10%
MDL Corp	315-0126 – 12.3V	Magnetic		26%	32%				9%	8%
Orientronic	DLR1250BN	Magnetic	13%	27%	27%	27%		8%		
Q-Tran	Q6S-DC-120-12 (Rectified)	Magnetic	13%	21%	21%	21%		10%		
Q-TRAN	QT10-120/12-TP-RC	Magnetic	9%	24%	24%	24%		8%		
Q-TRAN	QT20-120/12-TP-RC	Magnetic	9%	28%	28%	28%		9%		
Q-Tran	QT50-75CK-PT-277-RC	Magnetic								
Q-TRAN	QT-50-75CK-PT-RC Date 11/11	Magnetic	10%	23%	23%	23%		1 Lamp: NC 2,3 Lamps: 20%		
Q-TRAN	QT50SV-120/12-RC	Magnetic	13%	30%	30%	30%				
Q-Tran	QTM60-DC+CAP (Rectified + Filtered)	Magnetic	10%	NC	NC	NC		1 Lamp: 10% 2,3 Lamps: 34%		

Transformer	Dimmer -->		Creston CLS-C6(Any Suffix)	Creston CLS-EXP-DIM	Creston CLS-EXP-DIMU	Creston CLX-3DIM5, CLX-1DIM8, CLX-2DIM2, CLX-2DIM8	Creston CLS-1DEVL4	Creston DIN-1DIM4	Creston DIN1DIMU4	Creston CLW-DIM(Any suffix), P-DIMEX	Creston GLX-DIM6	Creston GLX-2DIM8	Creston CLW-DEVELOX(Any suffix)	Forbes & Lomax FLE603P
North America														
TechnoMagnet	ODC75S12	Magnetic	12%	10%	NC	14%	NC	8%	NC	8%	8%	8%	NC	

Notes: Compatibility tests are conducted by Soraa only as guidance for the user
 All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site
 Results may vary due to variability in component choices and manufacturing processes by the dimmer or transformer manufacturer
 if the transformer's minimum wattage is not met, the lamp may only operate under nominal conditions (nominal line voltage and thermal conditions where the lamp is at full power).
 if the fixture/transformer is not listed as tested, please consult with Soraa first before making any recommendations to end customer.

	Dims to < 20%
NC	Not compatible
	Not tested