

# 90+ LIGHTING



MODEL	PAR38 15W 1050LM 2700K E26
SKU	SE-RL6.CF11.1415G

DIMMER COMPATIBILITY LIST				
MANUFACTURER	BRAND	DIMMER MODEL	COMPATIBILITY	
LUTRON	DIVA	DV-603P	OK	
		DVWCL-153PH-WH	OK	
		DVW-600PH-WH	NC	
		DV-600PH-WH	NC	
		DVCL-153PH	NC	
		DV-603PH-WH	OK	
		DVCL-153P-WH	OK	
		DVWCL-153PH-WHC	NC	
		DV-600P-WH	OK	
		DVCL-253PH	NC	
		DVCL-153P-WH	NC	
		DVELV-300P-WH	OK	
		-	S-600	OK
		SKYLARK	CTCL-153P-WH	OK
			S-600PR-WH	NC
	S-603PGH-WH		NC	
	S-600H-WH		OK	
	S-10PH		NC	
	SCL-153P-WH		NC	
	S-600-IV		NC	
	S-600-AL		OK	
	S-603PH-WH		OK	
	S-600P-WH		OK	
	SCL-153PH-WH		NC	
	S-603P-WH		OK	
	SELV-300P-WH		OK	
	SLV-600-WH		OK	
	-		D-600PH-DK	NC
	MAESTRO	MAW-600	NC	
		MAW-600H-AL	NC	
		MACL-153M-WH	OK	
		MACL-153MR-WH	OK	
		MACL-153MH-WH	OK	
		MSCL-OP153MH-WH	NC	
		MACL-153MLH-WH	OK	
		TG-603PGH-WH	NC	
		MAELV-600-WH	OK	
		-	DV-603PR	NC
		-	D-600RH-DK	OK
		TOGGLER	TG-600PH-WH	NC
			TG-600PH-IV	OK
			TGCL-153PH-WH	OK
		-	D-600R-WH	OK
	-	D-600R-IV	OK	
	ARIADNI	AYCL-153P-WH	OK	
		AY-600PH-WH	NC	
		AYCL-153PH	OK	
	VIVE	MRF2S-6CL-WH	OK	
	CASETA	PD-6WCL-WH	OK	
	SPACER	SPSELV-600M	OK	
	NOVA T	NTELV-300-WH	OK	
		NTLV-600-277-WH	OK	
	RADIO RA2	RRD-6CL-WH	OK	
	DECORA	R62-6674-POW	OK	
	LEVITON	-	6684	NC
		-	NO.6683	NC
		-	6631-LA	OK
		-	IPI06	NC
		-	S-600P-WH	OK
		-	NO.6672	NC
-		603-6631-A	OK	
-		6631-A	OK	
-		NO.IPL06	NC	
-		IPI10-1LZ	NC	
-		6683-10Z	NC	
-		IPI06-1LZ	NC	
-		NO.6631	OK	
-		6681	NC	
-		S-600P-WH	OK	
GE		-	18024	NC
ALMOND		-	LUXDM600-12	NC
CTL		-	DM600-12-3	OK
AH	-	SDM3/1000	OK	
LEGRAND	-	SDM/600	OK	
	-	HCL453PTC	NC	
COOPER	-	DAL06P-C2-K	NC	
	-	TAL06P-C2-K	NC	
	-	SAL06P-W-K	NC	
MAXXIMA	-	AAL06-C1	NC	
	-	MEW-DM600	NC	

### DIMMER COMPATIBILITY

OK
OK
NC

Dims to < 15%  
 Dims to 15 - 30%  
 Not Compatible

### 90+ LIGHTING NOTES

- 1) This dimmer compatibility chart is provided by 90+ Lighting as a guidance for selecting a dimmer and lamp combination.
  - 2) The results may be different for each application depending on the installation conditions.
  - 3) 90+ Lighting recommends to perform a previous test before the installation to verify the dimmer compatibility.
  - 4) We recommend using a 1/5 loading factor for incandescent dimmers when using with 90+ lamps.
- For example: a 400W dimmer should be loaded with a number of lamps whose combined power do not exceed 80W.