

Lightology

2-Circuit Monorail 300W Single Feed Surface Transformer

SPEC #

TLG12095




BRAND Visual Comfort Modern

DESCRIPTION

2-Circuit 300 Watt single-feed surface transformer converts standard 120 line voltage to 12 volts to provide the necessary voltage for powering a two-circuit monorail low-voltage system. It can power lamps totaling up to 300 watts with 150 watts maximum on each circuit. Transformer is concealed inside a decorative housing with a fast acting secondary circuit breaker that will safely turn the system off should a short occur. Breaker can be reset once the short has been removed. Black and White finishes have Satin Nickel feeds. The shortest rigid standoff that can be used with this transformer is the 6 inch rigid standoff. Use low voltage magnetic dimmer to dim. ETL listed. 9.1 inch diameter x 5.8 inch height.



SHADE COLOR	Satin Nickel
BODY FINISH	Chrome
WATTAGE	300W
DIMMER	Low Voltage Magnetic
DIMENSIONS	9.1"L x 9.1"W x 5.8"H
LAMP	N/A
SPEC #	TLG12095



COMPANY	PROJECT	FIXTURE TYPE	APPROVED BY	DATE