

Lightology

lightology.com
866-954-4489
07-30-26

Project: _____

Company: _____

Location: _____ Fixture Type: _____

SPEC #: **EDG53559**

Approved On: _____ Approved By: _____


Remote 4x300W 12V Dual Feed Plug-In Magnetic Transformer

By PureEdge Lighting



Description

Two 2X300 Watt Remote Plug-in Magnetic Transformers convert four line volt inputs into four low voltage 300 watt, 12 volt outputs for powering Monorail 2 Circuit system. The remote transformer must be installed in an accessible location (such as an attic or in a closet), and it is best to keep transformer within 20 feet of power canopy/junction box to prevent voltage drop. Protected by fast acting secondary circuit breaker. Dimmable using four 600 watt magnetic low voltage dimmers, sold separately. Some buzzing may occur on low levels and may be reduced with four dimming de-buzzing coils, sold separately. System not dimmable when one circuit uses halogen and the other circuit uses LED. All other combinations are dimmable. Requires dual power feed canopy, sold separately. ETL listed. 6 inch width x 9.5 inch length x 4.75 inch height.



Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	1200W
DIMMER	Low Voltage Magnetic
DIMENSIONS	9.5"L x 6"W x 4.75"H
BULB NOT INCLUDED	N/A

Notes:

--