


R3-509

3" SQUARE SHOWER TRIM



Project

Location



PRODUCT DESCRIPTION

3" Square Shower Trim with Frosted Glass (DAMP Location)

To be used in low and line voltage applications.

LAMPING: Accommodates an MR-16 or GU-10 bulb. Please see housing for maximum wattage allowed according to selection.

Painted finishes are powder coated for abrasion resistance, frosted lens included. Steel metal clips secure to housing.

DIAMETER: 3 3/4"

FINISHES: Matte White (MW), Brushed Nickel (BN)

MODEL	FINISH
R3-509	MW
	BN

COMPATIBLE HOUSINGS

Model	Description
R3-050	3" LOW VOLTAGE NON IC REMODEL HOUSING REMOTE TRANSFORMER (NOT SUPPLIED)50W MAX MR-16
R3-499AT	3" LOW VOLTAGE NON IC AIRTITE NEW CONSTRUCTION HOUSING 50W MAX MR-16
R3-499ICA	3" LOW VOLTAGE IC AIRTITE NEW CONSTRUCTION HOUSING 35W MAX MR-16
R3-499RAT	3" LOW VOLTAGE NON IC AIRTITE REMODEL HOUSING 50W MAX MR-16
R3-G19AT	3" LINE VOLTAGE NON IC AIRTITE NEW CONSTRUCTION HOUSING 50W MAX GU-10
R3-G19ICA	3" LINE VOLTAGE IC AIRTITE NEW CONSTRUCTION HOUSING 35W MAX GU-10
R3-G19RAT	3" LINE VOLTAGE NON IC AIRTITE REMODEL HOUSING 50W MAX GU-10