# **NS-41**

4" Stepped Baffle with Ring

Type **Project** Catalog No. **Notes** 

#### **FEATURES**

Trim: Precision spun 0.040 baffle with deep grooves to reduce aperture glare. Non-reflective painted finishes. Separate trim ring available in plastic or metal, may also be used with custom combination of ring finishes.

Mounting: Trim includes three trim clips that securely mount trim in housing.

# **COMPATIBLE LAMP / HOUSINGS**

#### Line Voltage:

15W R20/PAR20 max. (NS-401AT/IC) 35W R20/PAR20 max. (NFBIC-4INCATA) 50W R20/PAR20 max. (NS-401QAT; NSIC-401QAT; NSR-404QAT; NSRIC-404QAT) See individual housing specification sheets for more information.

### **LABELS AND LISTINGS**

· cULus Listed for Damp Location when used with compatible housing





# **PRODUCT IMAGES & DIMENSIONS**



NS-41




NS-41B





NS-41P



# 4" Black Stepped Baffle with Ring

NS-41 = 4" Black Stepped Baffle with White Metal Ring

NS-41B = 4" Black Stepped Baffle with Black Metal Ring

NS-41G = 4" Black Stepped Baffle with Gold Metal Ring

NS-41P = 4" Black Phenolic Stepped Baffle with White Plastic Ring

# **Compatible Housings**

Catalog No.

NFBIC-4INCATA = 2-Hour Fire Rated New Construction / 35W max.NS-4010AT = Non-IC Air-Tight New Construction / 50W max

NS-4010AT/IC = IC Air-Tight New Construction / 15W max NSIC-4010AT = IC Air-Tight New Construction / 50W max NSR-4040AT = Non-IC Air-Tight Remodel / 50W max

NSRIC-4040AT = IC Air-Tight Remodel / 50W max

Example: NS-41 = 4" Black Stepped Baffle with White Metal Ring

