

**Dimmer Compatibility Guide**

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>		
<b>Item Number:</b>	774148	774149
<b>Ordering Code:</b>	LED16A21/927/I/D/2	LED16A21/930/I/D/2
<b>Item Number:</b>		
<b>Ordering Code:</b>		

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IP106	Good	1	6	Dims down to 20%
		SureSlide	6633-P	Best	1	6	Dims down to 4%
		Vizia	VPI06-1LZ	Good	3	6	Dims down to 10%
	Lutron	Toggle	TG-600	Good	1	6	Dims down to 12%
		Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Bad	4	6	
	Legrand	Titan	CD703-PW	Good	1	6	Dims down to 23%
		Harmony	D703-PTC	Best	1	6	Dims down to 1%
		Harmony	H703-PTC	Best	1	6	Dims down to 5%
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Good	1	6	Dims down to 15%
		Decora	6672	Best	1	6	Dims down to 10%
	Lutron	Decora Slide	DSL06-1LZ	Good	1	6	Dims down to 15%
		Skylark	CTL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MAEL-153MLH	Best	1	6	Dims down to 10%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggle	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 7%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 7%
		Harmony	HCL453PTC	Good	1	6	Dims down to 15%
		Adorne Paddle	ADPD453LM2	Bad	1	6	Dims down to 50%
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Dims down to 20%
		IlumaTech	IPE04	Good	1	6	Dims down to 12%
	Lutron	Decora	6615-P	Bad	1	6	Dims down to 60%
		Skylark Countour	CTELV-303P	Good	1	6	Dims down to 14%
		Diva	DVELV-300P	Good	1	6	Dims down to 14%
		Maestro	MAELV-600	Good	1	6	Dims down to 12%
		Skylark	SELVB-300P	Good	1	6	Dims down to 14%
		Skylark	VTELV-600M-W	Good	1	6	Dims down to 14%
		VIERTI	VTELV-600M-W	Good	1	6	Dims down to 14%
		Scene Director	SCELV	Bad	1	6	Dims down to 35%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 11%
		Decora	6613-P	Best	1	6	Dims down to 10%
	Lutron	Maestro	MALV-600	Not Compatible	6	6	Lamps did not turn on with 1-6
		Harmony	DLV703-PW	Best	1	6	Dims down to 4%
Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 23%	
	Titan	CDLV703-PW	Good	1	6	Dims down to 23%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Bad	1	6	Dims down to 35%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dims down to 20%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims down to 14%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 20%
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1				
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1				
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 2%
Universal	Legrand	Adorne SofTap	ADTP703TU	Bad	1	6	Dims down to 30%
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1%
		Harmony	H703PTUTC	Bad	1	6	Dims down to 30%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 1%
		Decorators	DAL06P-CZ-K-L	Best	1	6	Dims down to 1%
	Cooper	Decorators	DAL06P-CZ-K-L	Best	1	6	Dims down to 1%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

<b>Overall Rating</b>	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 10% or less of light output for JAS.
<b>High End (H.E.) Dead Travel</b>	
<b>Low End (L.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.