

HPDx-CC

RECOMMENDED DIMMER LIST*

BRAND	MODEL #	DIMMER SPECS	GRADE	DIMMING RANGE (%)	MAX LOAD
Dals	SM-DIMSW Smart Dimmer	Triac, 250W LED/CFL	Compatible	Min: 6 / Max: 100	8
Lutron	DVCL-153PR-WH-C	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 5 / Max: 100	5
Lutron	CTCL-153PDH-WH-C	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 5 / Max: 100	5
Lutron	STCL-153PH-WH-C	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 1 / Max: 100	5
Lutron	DVWCL-153PH-WHC	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 5 / Max: 100	5
Lutron	MACL-153MRHW-WHC	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 1 / Max: 100	5
Lutron	DVELV-300P-WH	300W electronic low voltage dimmer	Compatible	Min: 7 / Max: 93	10
Lutron	MA-PRO-WH	ELV, 250W LED/CFL	Compatible	Min: 2 / Max: 100	8
Lutron	Caseta PD-6WCL-WH-R-C	Triac, 300W Dimmable CFL/LED	Compatible	Min: 2 / Max: 100	10
Lutron	Caseta PD-5NE-WH-C	ELV, LED—up to 250 W	Compatible	Min: 3 / Max: 100	8
Lutron	Caseta PD-10NXD-WH	Triac, LED—up to 250 W	Compatible	Min: 1 / Max: 100	5
Leviton	6672-1LW	Triac, 150W Dimmable CFL/LED	Compatible	Min: 25 / Max: 100	5
Leviton	DSM10	Triac, 450W Dimmable CFL/LED	Compatible	Min: 19 / Max: 100	15
Leviton	6674	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 7 / Max: 100	5
Leviton	IPL06-10Z	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 13 / Max: 100	5
Leviton	DSL06-752	Triac, 150 W Dimmable CFL/LED	Compatible	Min: 12 / Max: 100	5
Leviton	D26HD-742-1RW	Triac, 300W LED/CFL	Compatible	Min: 9 / Max: 100	10
Legrand	RHCL453PNICCV4	Triac, 450W Dimmable CFL/LED	Compatible	Min: 10 / Max: 100	15
Legrand	ADTP703TUM4	Triac,450W Dimmable CFL/LED	Compatible	Min: 3 / Max: 100	15
Legrand	ADPD453LM2	Triac,450W Dimmable CFL/LED	Compatible	Min: 34 / Max: 100	15
Legrand	RHL373PW	Triac, 250W LED	Compatible	Min: 7 / Max: 100	8
Control 4	C4-APD120-WH	ELV, 120W LED	Compatible	Min: 5 / Max: 100	4
Control 4	C4-FPD120-WH	Triac, 200W LED	Compatible	Min: 1 / Max: 100	6

HPDx-CC-V

RECOMMENDED DIMMER LIST*

BRAND	MODEL #	DIMMER SPECS	GRADE	DIMMING RANGE (%)	MAX LOAD
Lutron	DVSTV (0–10 V Controls)	960W, Operating Voltage:120–277 V~, Load Switching, Capacity: 8 A	Compatible	Min: 0 / Max: 100	32

* Minimal buzzing noise may occur with some dimmers