

### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	Filaments: Fully Compatible Dimming						
<b>Item Number:</b>	776603*	776604*	776606*	776655*	776658*	776661	776674
<b>Ordering Code:</b>	LED2CA10/22K/FIL-NOS/2	LED276/22K/FIL-NOS/2	LED2G16/22K/FIL-NOS/2	LED2B11/27K/FIL/E12/2	LED2CA10/27K/FIL/E12/2	LED2CA10/27K/FIL/E12/F/2	LED2B11/27K/FIL/E12/F/2
<b>Item Number:</b>	776855						
<b>Ordering Code:</b>	LED2B11/27K/FIL/3						

Lamps per Dimmer								
	Manufacturer	Product	Model Number	Overall Rating	Min	Max*	Notes	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	illumaTech	IPI06	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%	
		SureSlide	6633-P	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%	
		Vizia	VPI06-1LZ	Good	1	6	Minor flicker at Medium with 1, 2+ best dims down to 1%	
	Lutron	Toggle	TG-600	Good	1	6	Shimmer at Med with 1, 2+ best dims down to 1%	
		Divva	DV-600	Good	1	6	2+ minimum load, 3+ best dims down to 1%	
		Skylark	S-600	Best	1	6	Dims down to 1%	
	Legrand	Maestro	MAW-600	Bad	1	6	5+ minimum load	
		Titan	CD703-PW	Bad	1	6	Flicker at HE 1-2, 4+ best dims down to 1%	
		Titan	CDLV703-PW	Bad	1	6	Flicker at Med 1-3, 4+ best dims down to 1%	
		Harmony	D703-PTC	Bad	1	6	Flicker at Med to HE 1-3, 4+ best dims down to 1%	
	Harmony	HT03-PTC	Good	1	6	Flicker at Med to HE 1, 2+ best dims down to 1%		
CFL/LED	Leviton	illumaTech	IPL06	Best	1	6	Dims down to 1%	
		SureSlide	6674	Best	1	6	Dims down to 1%	
		Decora	6672	Best	1	6	Dims down to 1%	
	Lutron	Divva	DVCL-153PL	Good	1	6	Minor flicker 1-2, 3+ best dims down to 1%	
		Toggle	TGCL-153PH	Good	1	6	Minor flicker 1-2, 3+ best dims down to 1%	
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%	
		Skylark	CTCL-153	Good	1	6	Minor flicker 1-2, 3+ best dims down to 1%	
		Skylark	SCL-153P	Best	1	6	Dims down to 1%	
		Radio RA	RA2R-6CL-PD	Best	1	6	Dims down to 1%	
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 1%	
		Harmony	HCL453PTC	Best	1	6	Dims down to 1%	
		Adorne Paddle	AOPP453UM2	Best	1	6	Dims down to 5%	
	Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
			illumaTech	IPE04	Good	1	6	Minor flicker at LE 1, minor flicker at Med 1-6, dims down 1%
		Lutron	Decora	6615-P	Good	1	6	Minor flicker at LE 1-6, dims down 15%
Skylark			SELV-300P	Good	1	6	Shimmer at Med 1-2, dims down to 1%	
Skylark Countour			CTELV-303P	Good	1	6	Shimmer at Med 1-3, dims down to 1%	
Divva			DVELV-300P	Good	1	6	Shimmer at Med 1, dims down to 1%	
Maestro			MAELV-600	Best	1	6	Dims down to 1%	
VIERTI			VTEL-600M-W	Best	1	6	Dims down to 1%	
Legrand		Scene Director	SECLV	Best	1	6	Dims down to 1%	
		Magnetic Low Voltage	Vizia	VPM-06	Good	1	6	Minor flicker at Med 1-2, 3+ best dims down to 1%
Decora	6613-P		Good	1	6	Minor flicker at Med 1-2, 3+ best dims down to 1%		
Maestro	MALV-600		Bad	1	6	5+ minimum load, dims down to 5%		
Harmony	DLV703-PW		Good	1	6	Minor flicker at Med 1, 2+ best dims down to 1%		
Universal	Legrand	Adorne SoftTap	ADTP7703TU	Best	1	6	Dims down to 1%	
		Miro Decorator	DRD4-W	Good	1	6	Minor flicker at LE 1-3	
		Harmony	H703PTUC	Best	1	6	Dims down to 10%	
		Adorne Whisper	ADWR700MMTUM2	Best	1	6	Dims down to 1%	
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%	
		Decorator	DAL06P-C2-K-L	Good	1	6	Minor flicker at LE 1-6, dims down to 5%	
		Skye	SAL06P-W-K-L	Good	1	6	Minor flicker at LE 1-6, dims down to 5%	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

#### Overall Rating

<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	

Contact Information:  
 Bulbrite Industries Inc.  
 145 West Commercial Avenue Moonachie, New Jersey 07074  
 PHONE: 1-800-528-5555  
 FAX: 1-800-441-7708  
 Email: ProductSupport@bulbrite.com