



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	772297	772298	772301	772302
Item Number:	LED15PAR38/NF25/927/WD/2	LED15PAR38/FL40/927/WD/2	LED15PAR38/NF25/930/WD/2	LED15PAR38/FL40/930/WD/2
Ordering Code:				
Item Number:				
Ordering Code:				

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Best	1	6	Dims down to 10%	
		SureSlide	6633-P	Good	1	6	Dims down to 1%, dead travel LE to Med with 1-6, flicker LE with 1	
		Vizia	VPI06-1LZ	Not compatible	1	6	Ghosting with 1-6	
	Lutron	Toggler	TG-600	Good	1	6	Dims down to 1%, dead travel LE to Med with 1-6, flicker LE with 1	
		Lumea	LGCL-600	Good	1	6	Dims down to 1%, dead travel LE to Med with 1-6, flicker LE with 1	
		Diva	DV-600	Good	1	6	Dims down to 1%, dead travel LE to Med with 1-6, flicker LE with 1	
		Skylark	S-600	Good	1	6	Dims down to 1%, dead travel LE to Med with 1-6, flicker LE with 1	
		Maestro	MAW-600	Not compatible	1	6	Ghosting with 1-6	
	Legrand	Titan	CD703-PW	Good	1	6	Dims down to 7%, minor flicker at LE with 1-6	
		Harmony	H703-PTC	Good	1	6	Dims down to 1%, dead travel LE to Med with 1-6, flicker LE with 1	
			Harmony	H703-PTC	Good	1	6	Dims down to 1%, dead travel LE to Med with 1-6, flicker LE with 1
	CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 1%
SureSlide			6674	Best	1	6	Dims down to 1%	
Decora			6672	Best	1	6	Dims down to 1%	
Decora Slide			DSL06-1LZ	Best	1	6	Dims down to 1%	
Lutron		Skylark	CTCL-153	Best	1	6	Dims down to 1%	
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%	
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%	
		Skylark	SCL-153P	Best	1	6	Dims down to 1%	
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%	
Legrand		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%	
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%	
		Harmony	HCL453PTC	Best	1	6	Dims down to 1%	
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 22%	
Electronic Low Voltage	Leviton	Vizia	VPED4	Not compatible	1	6	Flickering from LE to Med with 1-6	
		IlumaTech	IPE04	Not compatible	1	6	Flickering from LE to Med with 1-6	
	Lutron	Decora	6615-P	Not compatible	1	6	Flickering from LE to Med with 1-6	
		Skylark Countour	CTELV-303P	Bad	1	6	Flickering Med with 1-6	
		Diva	DVELV-300P	Bad	1	6	Flickering Med with 1-6	
		Maestro	MAELV-600	Bad	1	6	Flickering Med with 1-6	
		Skylark	SELVB-300P	Bad	1	6	Flickering Med with 1-6	
		VIERTI	VTEL-600M-W	Bad	1	6	Flickering Med with 1-6	
		Legrand	Scene Director	SCELV	Not compatible	1	6	Flickering from LE to HE with 1-6
Magentic Low Voltage	Leviton	Vizia	VPM-06	Not compatible	1	6	Ghosting with 1-6	
		Decora	6613-P	Bad	1	6	Death travel from LE to Med with 1-6, flicker at Med with 1-6	
	Lutron	Maestro	MALV-600	Not compatible	1	6	Doesn't turn on with 1-6	
		Harmony	DLV703-PW	Good	1	6	Death travel from LE to Med with 1-6, flicker at LE with 1-6	
		Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 10%, minor flicker at LE with 1
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims down to 11%	
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 8%	
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 8%	
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 8%	
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 8%, minor flicker at LE with 1-6	
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%	
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6	Dims down to 15%	
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1%	
		Harmony	H703PTUTC	Not compatible	1	6	Flicker from LE to HE with 1-6	
		Adorne Whisper	ADWR700MMTUM2	Best	1	6	Dims down to 1%	
		Adorne Touch	ADTT700MMTUM2	Best	1	6	Dims down to 1%	
	Cooper	Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 1%	
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 1%	
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 10% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact Information:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-538-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.