



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:
Item Number: 770630
Ordering Code: LED5E11/30K/120/D

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
					Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Good	1	6	Dims down to 0.1%, minor flicker at 10% with 1	
		Sureslide	6633-P	Good	1	6		
		Vizia	VPI06-1LZ	Good	1	6		
	Lutron	Toggle	TG-600	Good	1	6	Dims down to 0.1%, minor flicker at 100% & 30% with 1	
		Oiva	OIV-600	Good	1	6		
		SkyLark	S-600	Good	1	6		
		Maestro	MAAV-600	Bad	6	6		
	Legrand	Titan	CD703-PW	Bad	1	6	Flicker at 5% with 1, flicker at Med & LE with 2, flicker at LE with 3	
		Harmony	D703-PTC	Bad	1	6		
		Harmony	H703-PTC	Bad	1	6		
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 0.1% with 1-6	
		Sureslide	6674	Best	1	6		
		Decora	6672	Best	1	6		
	Lutron	SkyLark Countour	CTCL-153	Good	1	6	Dims down to 0.1% with 1-6, minor flicker Med with 1	
		Oiva	DVCL-153PL	Best	1	6		
		Maestro	MACL-153MLH	Best	1	6		
		SkyLark	SCL-153P	Best	1	6		
		Toggle	TGCL-153PH	Best	1	6		
		Radio RA	RA2RR-6CL-PD	Best	1	6		
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 0.1% with 1-6	
		Harmony	HCL453PTC	Best	1	6		
		Adorne Paddle	ADPD453LM2	Good	1	6		
								Dims down to 10% with 1-6, minor flicker at 50% & 90% with 1
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 0.1% with 1-6	
		IlumaTech	IPE04	Best	1	6		
		Decora	6615-P	Good	1	6		
	Lutron	SkyLark Countour	CTELV-303P	Best	1	6	Dims down to 0.1% with 1-6	
		Oiva	OVELV-300P	Best	1	6		
		Maestro	MAELV-600	Best	1	6		
		SkyLark	SELV-300P	Best	1	6		
	Legrand	VERTI	YTELV-600M-W	Best	1	6	Dims down to 0.1% with 1-6	
		Scene Director	SCELV	Best	1	6		
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 0.1% with 1-6, Flicker at 20% with 4	
		Decora	6613-P	Good	1	6		
	Lutron	Maestro	MALV-600	Bad	6	6	Dims down to 0.1% with 6	
		Harmony	DLV703-PW	Bad	1	6		
		Titan	CDLV703-PW	Bad	1	6		
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 0.1% with 1-6	
	Leviton	Decora Smart Wi-Fi	DX6HD-18Z	N/A				
	Insteon	SwitchLin Remote Control dimmer		N/A				
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6		
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A				
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A				
	GE	Z WAVE	ZW3005	Best	1	6		
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 4% with 1-6	
		Miro Decorator	DRD4-W	Best	1	6		
		Harmony	H703PTUTC	Best	1	6		
		Adorne Whisper	ADWR700MMTUW2	Best	1	6		
	Cooper	Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 0.1% with 1-6	
		Decorator	DAL06P-C2-K-L	Good	1	6		
		Skye	SAL06P-W-K-L	Good	1	6		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	