BULBRITE turn life on

45 West Commercial Ave Ioonachie. NJ 07074 **Dimmer Compatibility Guide** Product Family Name: Item Number 776780 776791 LED4T6/27K/FIL/3 LED4T6/27K/FIL/3 Ordering Code: Item Number: Ordering Code: Lamps per Dimmer nended Manufact Product Model Nu **Overall Ratin** Note IPI06 Dims down to 1% IllumaTech Best 6 Leviton Dead travel Med to LE with 1 6633-P SureSlide Good 1 6 VPI06-1LZ izia Good 6 Flickering at LE with 2 1 ogglei TG-600 Best 6 Dims down to 1% Dims down to 1% Lumea LGCL-600 Best 6 1 candescent/Halogen (Triac/Pha Cut/Leading Edge Dimmers) Lutron DV-600 Best Dims down to 1% Diva 6 Skylark S-600 Best 6 Dims down to 1% 1 Not compatible Maestro MAW-600 1 6 Not works with full range dimming with 1-3 CD703-PW Titan Bad 4 6 Not works with full range dimming with 1-3 Legrand Harmony D703-PT0 Bad 4 6 Harmony H703-PTC Bad 6 Not works with full range dimming with 1-3 4 IllumaTech IPL06 Best Dims down to 1% 1 6 Sureslide 6674 Best 6 Dims down to 1% 1 Levitor 6672 Decora Best 1 6 Dims down to 1% ecora Slide DSL06-1LZ Best 6 Dims down to 1% Skylark CTCL-153 Best 6 Dims down to 1% Diva DVCL-153PI Best Dims down to 1% 6 CFL/LED Maestro MACL-153MLH Best 1 6 Dims down to 1% Lutron Skylark SCL-153P Dims down to 1% Best 1 6 TGCL-153PH Best Toggler 1 6 Dims down to 1% Radio RA RA2RR-6CL-PD Dims down to 1% Best 1 6 Harmon DCL453-PTC Best 6 Dims down to 1% 1 Legrand Radiant RHCL453PW Best 6 Dims down to 1% 1 Adorne Padd ADPD453LM2 Best Dims down to 1% 1 6 VPE04 Dims down to 1% Vizia Best 6 1 Levitor IPE04 Reverse dimming from HE to Med IllumaTec Good 1 6 6615-P Reverse dimming from HE to Med. Dims down to 35% Decora Bad 6 Skylark Countour CTELV-303P Best 1 6 Dims down to1% Electronic Low Voltage DVELV-300 Best Diva Dims down to1% Dims down to1% Lutron Maestro MAELV-600 Best 1 6 SELVB-300P Dims down to1% Skylark Best 6 1 /IERTI VTEL-600M-\ Best 6 1 Dims down to1% SCELV Legrand cene Directo Bad Flickering at HE with 1-6.dims down to 3% 6 VPM-06 Good Flickering at HE with 1-6 Vizia 1 6 Leviton ecora 6613-P Best Dims down to 1% Magentic Low Voltage Lutron Maestro MALV-600 Not compatibl 6 1 DLV703-PW Harmony Good 6 Dims down to 1% 2 Legrand Titan CDLV703-PW Dims down to 1% Good DDMX1-BLZ Decora Digital (Bluetooth) Best Dims down to 1% Leviton 1 6 Decora Smart Z-Wave Technology DZ6HD 6 Leviton Best 1 Dims down to1% Levitor Decora Smart WiFi Technology DW1KD Best Dims down to1% Smart Dimmer PD-10NXD Dims down to1% Lutron Caseta Wireless smart dimmer Wi-Fi Best 1 6 Lutron Caseta Wireless smart dimmer Wi-Fi PD-6WCL Best 6 Dims down to1% 1 GE Z WAVE ZW3005 Good 1 6 Minor flickering at LE with 1-6 ADTP703TU Adorne SofTap Good 3 Dims down to 16% 6 Miro Decorator DRD4-W Not compatib 6 It doesn't turn off with 1-6 1 Legrand Harmony H703PTUTO Bad 3 6 Dims down to 25% Adorne Whispe ADWR700MMTUW2 Best 1 6 Dims down to 1% dorne Touch ADTH700MMTUM2 Best Dims down to 1% 6 Decorator DAL06P-C2-K-L Good 2 6 Dims down to 1% Cooper SAL06P-W-Goo ims down to 1% Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer. tMay experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they vere initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level. **Overall Rati** Not Compatible One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off. One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth. Bad One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light leve Good These periods of dead travel are minor and most of the time not visible. Minor audible noise Best Most of the followin observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output. High End (H.E.) Dead Travel Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level. Low End (L.E.) Dead Travel

ontact Information Bulbrite Industries Inc. 145 West Commercial Avenue Moonachie, New Jersey 07074 HONE: 1-800-528-5555 FAX: 1-800-441-7708 mail: ProductSupport@bulbrite.com 2017 Bulbrite industries inc. All Rights Reserved.

achie. NJ 07074							
chie. No. 07074		D ¹		0.11			
		PLEASE NOTE: Compatibility list is based upon testing co	r Compatibility		Actual results may vary.		
uct Family Name:							
Number: ering Code:	776729 LED4T6/27K/FIL/M/3	776730 LED4T6/30K/FIL/M/3					
Number:	LED410/2/K/FIL/W/3	LEU416/3UK/FIL/W/3					
ring Code:							
					Lamps p Recommended	er Dimmer	
	Manufacturer	Product	Model Number	Overall Rating	Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Dims down to 1%, not smooth dimming
		SureSlide Vizia	6633-P VPI06-1LZ	Best Good	1 2	6	Dims down to 1% Dims down to 1%
		Toggler	TG-600	Best	1	6	Dims down to 1%
		Lumea	LGCL-600	Best	1	6	Dims down to 1%
	Lutron	Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
	Legrand	Maestro Titan	MAW-600 CD703-PW	Good Good	4	6	Dims down to 1%, Dims down to 11%
		Harmony	D703-PTC	Good	4	6	Dims down to 1%
		Harmony	H703-PTC	Good	4	6	Dims down to 1%
	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
CFL/LED		Sureslide	6674	Best	1	6	Dims down to 1%
		Decora Decora Slide	6672 DSL06-1LZ	Best Best	1	6	Dims down to 1% Dims down to 1%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Sunnata	STCL - 153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler Radio RA	TGCL-153PH RA2RR-6CL-PD	Best Best	1	6	Dims down to 1% Dims down to 1%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
	Legrand	Radiant	RHCL453PW	Best	1	6	Dims down to 1%
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%
				-			
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 1%
		IllumaTech Decora	IPE04 6615-P	Bad Bad	1	6	Reverse dimming from HE to Mid No dimming range
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%
		Diva	DVELV-300P	Best	1	6	Dims down to 1%
		Maestro	MAELV-600	Best	1	6	Dims down to 1%
		Skylark	SELVB-300P	Best	1	6	Dims down to 1%
	t a surra d	VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
	Legrand	Scene Director	SCELV	Not compatible	1	6	Flickering at HE with 1-6
Magnetic Low Voltage		Vizia	VPM-06	Good	2	6	Dims down to 1%
	Leviton	Decora	6613-P	Best	1	6	Dims down to 1%
	Lutron	Maestro	MALV-600	Not compatible	1	6	Not turning on with 1-6
		Harmony	DLV703-PW	Good	2	6	Dims down to 1%
	Legrand	Titan	CDLV703-PW	Good	3	6	Dims down to 1%
	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1%
Smart Dimmer	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%
Universal	Legrand	Adorne SofTap	ADTP703TU	Good	2	6	Dims down to 1%
		Miro Decorator	DRD4-W	Good	2	6	Dims down to 1%
		Harmony	H703PTUTC	Bad	2	6	Dims down to 1%, flickering at LE with 1-6
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%,not smooth dimming
	-	Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1%, not smooth dimming
			ult dimmer manufacturer				
experience "pop-on", lights cannot be		er system. For maximum capacity please consults level. The slider needs to be raised above the nmer cannot be turned on to just the minimum	minimum light level for the	lights to first turn on if	they		
<pre>xperience "pop-on", lights cannot be itially off. Then, the slider can be low</pre>	turned on immediately to their minimur	n level. The slider needs to be raised above the	minimum light level for the	lights to first turn on if	they		
perience "pop-on", lights cannot be tially off. Then, the slider can be lov I Rating	turned on immediately to their minimur rered to get to a lower light level; the dir	n level. The slider needs to be raised above the	minimum light level for the I level.				

One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise. Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output. Best High End (H.E.) Dead Travel Low End (L.E.) Dead Travel Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level. Contact Information: Bulbrite Industries Inc. 135 West Commercial Avenue Moonachie, New Jersey 07074 PHONE: 1-800-528-5555 FAX: 1-800-451-7708 Email: ProductSupport@bulbrite.com #2.021/ support@bulbrite.com #2.021/ support@bulbrite.com #2.021/ support@bulbrite.com #2.021/support@bulbrite.com #2.021/support@bu