



145 West Commercial Ave.  
Moonachie, NJ 07074

### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	773210	773211	773212
<b>Item Number:</b>	LED9/BOXDL/4/827/WHRD/D	LED9/BOXDL/4/830/WHRD/D	LED9/BOXDL/4/840/WHRD/D
<b>Ordering Code:</b>			
<b>Item Number:</b>			
<b>Ordering Code:</b>			

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum		Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	JPI05	Best	1	6		Dims down to 10%
		SureSlide	6633-P	Best	1	6		Dims down to 4%
		Vizia	VPI06-1LZ	Good	4	6		Dims down to 4%
	Lutron	Toggle	TG-600	Best	1	6		Dims down to 9%
		Diva	DV-600	Best	1	6		Dims down to 1%
		SkyLark	S-600	Best	1	6		Dims down to 3%
		Maestro	MAW-600	Good	4	6		Dims down to 3%
	Legrand	Titan	CD703-PW	Good	1	6		Dims down to 12%, flicker at LE with 1
		Harmony	D703-PTC	Best	1	6		Dims down to 1%
		Harmony	H703-PTC	Best	1	6		Dims down to 5%
CFL/LED	Leviton	IllumaTech	JPL06	Best	1	6		Dims down to 1%
		Sureslide	6674	Best	1	6		Dims down to 6%
		Decora	6672	Good	1	6		Dims down to 7%
	Lutron	Decora Slide	DSL06-1LZ	Best	1	6		Dims down to 6%
		SkyLark	CTCL-153	Best	1	6		Dims down to 1%
		Diva	DVCL-153PL	Best	1	6		Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6		Dims down to 4%
		SkyLark	SCL-153P	Best	1	6		Dims down to 1%
		Toggle	TGCL-153PH	Best	1	6		Dims down to 1%
	Legrand	Radio RA	RA2RR-GCL-PD	Best	1	6		Dims down to 2%
		Harmony	DCL453-PTC	Best	1	6		Dims down to 3%
		Harmony	HCL453PTC	Best	1	6		Dims down to 6%
		Adorne Paddle	ADPD453LM2	Good	1	6		Dims down to 20%
Electronic Low Voltage	Leviton	Vizia	VP604	Best	1	6		Dims down to 9%
		IllumaTech	JPE04	Best	1	6		Dims down to 6%
		Decora	6615-P	Bad	1	6		Dims down to 30%
	Lutron	SkyLark Countour	CTELV-303P	Best	1	6		Dims down to 7%
		Diva	DVELV-300P	Best	1	6		Dims down to 7%
		Maestro	MAELV-600	Best	1	6		Dims down to 6%
		SkyLark	SELVB-300P	Best	1	6		Dims down to 7%
	Legrand	VIERTI	VTEL-600M-W	Good	1	6		Dims down to 7%
		Scene Director	SCELV	Good	1	6		Dims down to 18%
Magenta Low Voltage	Leviton	Vizia	VPM-06	Good	4	6		Dims down to 4%
		Decora	6613-P	Best	1	6		Dims down to 5%
	Lutron	Maestro	MALV-600	Not compatible	1	6		Does not turn on / off with 1-6
		Harmony	DLV703-PW	Best	1	6		Dims down to 3%
Legrand	Titan	CDLV703-PW	Best	1	6		Dims down to 9%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6		Dims down to 10%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6		Dims down to 7%
	Leviton	Decora Smart Wi-Fi Technology	DW1KD	Best	1	6		Dims down to 10%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6		Dims down to 6%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6		Dimsdown to 4%
	GE	Z WAVE	ZW3005	Best	1	6		Dims down to 1%
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6		Dims down to 13%
		Miro Decorator	DRD4-W	Best	1	6		Dims down to 13%
		Harmony	H703PTUTC	Good	1	6		Dims down to 20%
		Adorne Whisper	ADWR700MMTUMZ	Best	1	6		Dims down to 1%
	Cooper	Adorne Touch	ADTH700MTUMZ	Best	1	6		Dims down to 1%
		Decorator	DAI06P-CZ-K-L	Best	1	6		Dims down to 1%
	Skye	SAL06P-W-K-L	Best	1	6		Dims down to 1%	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

<b>Overall Rating</b>	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	
<b>Low End (L.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Contact Information:  
 Bulbrite Industries Inc.  
 145 West Commercial Avenue  
 Moonachie, New Jersey 07074  
 PHONE: 1-800-528-5555  
 FAX: 1-800-443-7708  
 Email: ProductSupport@bulbrite.com  
 ©2017 Bulbrite Industries Inc.  
 All Rights Reserved.



145 West Commercial Ave.  
Moonachie, NJ 07074

### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	773220	773221	773222
<b>Item Number:</b>	LED14IBOXDL/6/827/WHRD/D	LED14IBOXDL/6/830/WHRD/D	LED14IBOXDL/6/840/WHRD/D
<b>Ordering Code:</b>			
<b>Item Number:</b>			
<b>Ordering Code:</b>			

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	illumaTech	IPIO6	Good	1	6	Dims down to 12%
		SureSlide	6633-P	Best	1	6	Dims down to 6%
		Vizia	VPI06-1LZ	Good	2	6	Dims down to 6%
	Lutron	Toggle	TG-600	Good	1	6	Dims down to 12%
		Diva	DV-600	Best	1	6	Dims down to 3%
		Skylark	S-600	Best	1	6	Dims down to 5%
		Maestro	MAW-600	Good	2	6	Dims down to 3%
	Legrand	Titan	CD703-PW	Good	1	6	Dims down to 15%
		Harmony	D703-PTC	Best	1	6	Dims down to 3%
		Harmony	H703-PTC	Best	1	6	Dims down to 8%
CFL/LED	Leviton	illumaTech	IPL06	Best	1	6	Dims down to 2%
		Sureslide	6674	Best	1	6	Dims down to 10%
		Decora	6672	Good	1	6	Dims down to 12%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 10%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 6%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggle	TGCL-153PH	Best	1	6	Dims down to 1%
	Legrand	Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 5%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 5%
		Harmony	HCL453PTC	Best	1	6	Dims down to 10%
		Adorne Paddle	ADPD453LM2	Bad	1	6	Dims down to 25%
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 10%
		illumaTech	IPE04	Best	1	6	Dims down to 7%
	Lutron	Decora	6615-P	Bad	1	6	Dims down to 30%
		Skylark Countour	CTELV-303P	Best	1	6	Dims down to 10%
		Diva	DVELV-300P	Best	1	6	Dims down to 10%
		Maestro	MAELV-600	Best	1	6	Dims down to 10%
		Skylark	SELVB-300P	Best	1	6	Dims down to 10%
		VIERTI	VTEL-600M-W	Good	1	6	Dims down to 20%
		Scene Director	SCELV	Good	1	6	
Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 5%
		Decora	6613-P	Best	1	6	Dims down to 8%
	Lutron	Maestro	MALV-600	Good	4	6	Dims down to 5%
		Harmony	DLV703-PW	Best	1	6	Dims down to 5%
Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 13%	
	Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6
Leviton		Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 10%
Leviton		Decora Smart Wi-Fi Technology	DW1KD	Best			Dims down to 10%
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 8%
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dimsdown to 9%
GE		Z WAVE	ZW3005	Best	1	6	Dims down to 2%
Universal	Legrand	Adorne SoftTap	ADTP703TU	Good	1	6	Dims down to 15%
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 2%
		Harmony	H703PTUTC	Good	1	6	Dims down to 20%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 2%
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 2%
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 2%
		Skylark	SAL06P-W-K-L	Best	1	6	Dims down to 2%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

<b>Overall Rating</b>	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	
<b>Low End (L.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Contact Information:  
Bulbrite Industries Inc.  
145 West Commercial Avenue  
Moonachie, New Jersey 07074  
PHONE: 1-800-528-5555  
FAX: 1-800-441-7708  
Email: ProductSupport@Bulbrite.com  
©2017 Bulbrite Industries Inc.  
All Rights Reserved.