

Dimmer Compatibility Guide

Product Family Name: Item Number: Ordering Code: Item Number: Ordering Code: 776502 LED4A19/22K/FIL-NOS

| | Manufacturer | Product | Model Number | Overall Rating | Recommended Minimum | Maximum Tested* | Notes |
|-----------------------------------|--------------|------------------------------------|---------------|--------------------------------|---------------------|-----------------|--|
| | Leviton | IllumaTech | IPI06 | Not Compatible | 1 | 6 | No dimming range |
| | | SureSlide | 6633-P | Not Compatible | 1 | 6 | No dimming range |
| | | Vizia | VPI06-1LZ | Not Compatible | 1 | 6 | No dimming range |
| | Lutron | Toggler | TG-600 | Not Compatible | 1 | 6 | No dimming range |
| Incandescent/Halogen (Triac/Phase | | Diva | DV-600 | Not Compatible | 1 | 6 | No dimming range |
| Cut/Leading Edge Dimmers) | | Skylark | S-600 | Not Compatible | 1 | 6 | No dimming range |
| | | Maestro | MAW-600 | Not Compatible | 2 | 6 | No dimming range |
| | Legrand | Titan | CD703-PW | Not Compatible | 1 | 6 | No dimming range |
| | | Harmony | D703-PTC | Not Compatible | 1 | 6 | No dimming range |
| | | Harmony | H703-PTC | Not Compatible | 1 | 6 | No dimming range |
| | | IllumaTech | IPL06 | Not Compatible | 1 | 6 | No dimming range |
| | Leviton | Sureslide | 6674 | Not compatible Not compatible | 1 | 6 | No dimming range |
| | | Decora | 6672 | Not compatible Not compatible | 1 | 6 | No dimming range No dimming range |
| | | Decora Slide | DSL06-1LZ | Not compatible Not compatible | 1 | 6 | No dimming range No dimming range |
| | | Skylark | CTCL-153 | Not compatible Not compatible | 1 | 6 | No dimining range No dimming range |
| | Lutron | Diva | DVCL-153PL | Not compatible Not compatible | | 6 | |
| CFL/LED | | | | | 1 | 6 | No dimming range |
| CFL/LED | | Maestro | MACL-153MLH | Not compatible | | | No dimming range |
| | | Skylark | SCL-153P | Not compatible | 1 | 6 | No dimming range |
| | | Toggler | TGCL-153PH | Not compatible | 1 | 6 | No dimming range |
| | | Radio RA | RA2RR-6CL-PD | Not compatible | 1 | 6 | No dimming range |
| | | Harmony | DCL453-PTC | Not compatible | 1 | 6 | No dimming range |
| | Legrand | Harmony | HCL453PTC | Not compatible | 1 | 6 | No dimming range |
| | | Adorne Paddle | ADPD453LM2 | Not compatible | 1 | 6 | No dimming range |
| | | Vizia | VPE04 | Good | 1 | 6 | Dims down to 1% with minor flickering at LE |
| | Leviton | IllumaTech | IPE04 | Good | 1 | 6 | Dims down to 1% with minor flickering at LE |
| | | Decora | 6615-P | Best | 1 | 6 | Dims down to 4% |
| | | Skylark Countour | CTELV-303P | Good | 1 | 6 | Dims down to 1% with minor flickering at LE |
| Electronic Low Voltage | Lutron | Diva | DVELV-300P | Good | 1 | 6 | Dims down to 1% with minor flickering at LE |
| | | Maestro | MAELV-600 | Good | 1 | 6 | Dims down to 1% with minor flickering at LE |
| | | Skylark | SELVB-300P | Good | 1 | 6 | Dims down to 1% with minor flickering at LE |
| | | VIERTI | VTEL-600M-W | Good | 1 | 6 | Dims down to 1% with minor flickering at LE |
| | Legrand | Scene Director | SCELV | Bad | 1 | 6 | Dims down to 1% with HE flickering |
| • | | | | | | | |
| Magentic Low Voltage | Leviton | Vizia | VPM-06 | Not Compatible | 1 | 6 | No dimming range |
| | Ecvitori . | Decora | 6613-P | Not comaptible | 1 | 6 | No dimming range |
| | Lutron | Maestro | MALV-600 | Not comaptible | 1 | 6 | No dimming range |
| | | Harmony | DLV703-PW | Not comaptible | 1 | 6 | No dimming range |
| | Legrand | Titan | CDLV703-PW | Not comaptible | 1 | 6 | No dimming range |
| | | | | | | | 1 |
| Smart Dimmer | Leviton | Decora Digital (Bluetooth) | DDMX1-BLZ | Good | 1 | 6 | Dims down to 1% with flickering at LE |
| | Leviton | Decora Smart Z-Wave Technology | DZ6HD | Good | 1 | 6 | Dims down to 1% with flickering at LE |
| | Lutron | Caseta Wireless smart dimmer Wi-Fi | PD-10NXD | Good | 1 | 6 | Dims down to 1% with flickering at LE |
| | Lutron | Caseta Wireless smart dimmer Wi-Fi | PD-6WCL | Not Compatible | 1 | 6 | lamp keep on / off |
| | Legrand | Adorne touch Wi-Fi TRU Universal | ADTH700RMTUW1 | | | | |
| | Legrand | Adorne Sof Tap Wi-Fi TRU Universal | ADTP700RMTUW1 | | | | |
| | GE | Z WAVE | ZW3005 | Good | 1 | 6 | Dims down to 1% with flickering at LE |
| Universal | Legrand | Adorne SofTap | ADTP703TU | Good | 2 | 6 | Dims down to 1% with shimmering at LE |
| | | Miro Decorator | DRD4-W | Good | 1 | 6 | Dims down to 1% with shimmering at LE |
| | | Harmony | H703PTUTC | Good | 2 | 6 | Dims down to 1% with shiffillering at LE Dims down to 20% |
| | | Adorne Whisper | ADWR700MMTUW2 | Good | 1 | 6 | Dims down to 20% Dims down to 1% with shimmering at LE |
| | | Adorne Wnisper Adorne Touch | ADTH700MMTUM2 | Good | 1 | 6 | Dims down to 1% with shimmering at LE Dims down to 1% with shimmering at LE |
| | Cooper | | DAL06P-C2-K-L | Good | 1 | 6 | |
| | | Decorator Skye | SAL06P-W-K-L | Good | 1 | 6 | Dims down to 1% with flickering at LE Dims down to 1% with flickering at LE |
| | | экуе | SALUOY-W-K-L | G000 | 1 | b | DITTIS GOWIT LO 1% WITH THEKETING AT LE |

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

| Overall Rating | | | | | |
|-----------------------------|--|--|--|--|--|
| Not Compatible | One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off. | | | | |
| Bad | One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth. | | | | |
| Good | One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise. | | | | |
| Best | Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output. | | | | |
| High End (H.E.) Dead Travel | Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level. | | | | |
| Low End (L.E.) Dead Travel | Determines now mount, in any, dead traver exists at the top and bottom of the diminishes stange. Dead traver is when the sincer can be intover without affecting the right level. | | | | |
| | | | | | |