



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: A-Type Dimmable: A21
Item Number: 774103 774113
Ordering Code: LED15A21/827/D LED15A21/830/D

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes
					Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IP106	Best	1	6	
		SureSlide	6633-P	Best	1	6	
		Vizia	VPI06-1LZ	Best	1	6	
	Lutron	Toggler	TG-600	Best	1	6	
		Diva	DV-600	Best	1	6	
		Skylark	S-600	Best	1	6	
		Maestro	MAW-600	Bad	1	6	2+ minimum load
	Legrand	Titan	CD703-PW	Best	1	6	
		Titan	CDLV703-PW	Best	1	6	
		Harmony	D703-PBKV	Best	1	6	
		Harmony	H703-PTC	Best	1	6	
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	
		Sureslide	6674	Best	1	6	
		Decora	6672	Best	1	6	
	Lutron	Diva	DVCL-153PL	Best	1	6	
		Toggler	TGCL-153PH	Best	1	6	
		Maestro	MACL-153MLH	Best	1	6	
		Skylark	CTCL-153	Best	1	6	
		Skylark	SCL-153P	Best	1	6	
		Radio	RA2RR-6CL-PD	Best	1	6	
	Legrand	Harmony	DCL453-PTC	Best	1	6	
Harmony		HCL453PTC	Best	1	6		
		Adorne Paddle	ADPD453LM2	N/A			
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	
		IllumaTech	IPE04	Best	1	6	
		Decora	6615-P	Bad	1	6	Dims down to 35% with 1-6
	Lutron	Skylark	SELVB-300P	Best	1	6	
		Skylark Countour	CTELV-300P	Best	1	6	
		Diva	DVELV-300P	Best	1	6	
		Maestro	MAELV-600	Best	1	6	
		VIERTI	VTEL-600M-W	Best	1	6	
	Legrand	Scene Director	SCELV300	Good	1	6	Dims down to 30% with 1-6
	Magnetic Low Voltage	Leviton	Vizia	VPM-06	Best	1	6
Decora			6613-P	Best	1	6	
Lutron		Maestro	MALV-600	Not Compatible	1	6	Can't turn on with 1-6
Legrand		Harmony	DLV703-PW	Best	1	6	
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	
		Miro Decorator	DRD4-W	Best	1	6	
		Harmony	H703PTUTC	Best	1	6	
		Adorne Whisper	ADWR700MMTUM2	Best	1	6	
		Adorne Touch	ADTH700MMTUM2	Best	1	6	
	Cooper	Decorator	DAL06P-C2-K-L	Best	1	6	
		Skye	SAL06P-W-K-L	Best	1	6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without
Low End (L.E.) Dead Travel	affecting the light level.