



## Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

**Product Family Name:** Reflectors Dimmable: BR30  
**Item Number:** 772810  
**Ordering Code:** LED16BR30/C/927/D

### Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Best	1	6	Dims down to 15%
		SureSlide	6633-P	Best	1	6	Dims down to 10%
		Vizia	VPI06-1LZ	Best	1	6	Dims down to 10%
	Lutron	Toggler	TG-600	Good	1	6	Slight hum , dims down to 20%
		Diva	DV-600	Good	1	6	Slight hum , dims down to 10%
		Skylark	S-600	Good	1	6	Slight hum , dims down to 10%
		Maestro	MAW-600	Good	1	6	Slight hum , dims down to 5%
		Radio RA	RA2RR-6CL-PD	Good	1	6	Slight hum , dims down to 8%
	Legrand	Titan	CD703-PW	Best	1	6	Dims down to 20%
		Titan	CDLV703-PW	Best	1	6	Dims down to 20%
Harmony		D703-PTC	Best	1	6	Dims down to 5%	
		Harmony	H703-PTC	Best	1	6	Dims down to 10%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 5%
		Sureslide	6674	Best	1	6	Dims down to 15%
		Decora	6672	Best	1	6	Dims down to 15%
	Lutron	Diva	DVCL-153PL	Good	1	6	Minor flicker at LE , slight hum ,dims down to 5%
		Toggler	TGCL-153PH	Good	1	6	Slight hum , dims down down to 5%
		Maestro	MACL-153MLH	Good	1	6	Slight hum , dims down to 5%
		Skylark	CTCL-153	Good	1	6	Slight hum , dims down to 5%
		Skylark	SCL-153P	Good	1	6	Slight hum , dims down to 5%
	Legrand	Radio RA	RA2RR-6CL-PD	Good	1	6	Slight hum , dims down to 8%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 10%
Harmony		HCL453PTC	Best	1	6	Dims down to 15%	
		Adorne Paddle	ADPD453LM2	N/A			
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 15%
		IllumaTech	IPE04	Good	1	6	Dims down to 10% , steppy dimming at LE
		Decora	6615-P	Bad	1	6	Dims down to 35%
	Lutron	Skylark	SELVB-300P	Best	1	6	Dims down to 10%
		Skylark Countour	CTELV-300P	Best	1	6	Dims down to 10%
		Diva	DVELV-300P	Best	1	6	Dims down to 10%
		Maestro	MAELV-600	Best	1	6	Dims down to 4%
	Legrand	VIERTI	VTEL-600M-W	Best	1	6	Dims down to 12%
Scene Director		SCELV	Good	1	6	Dims own to 25%	
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Best	1	6	Dims down to 10%
		Decora	6613-P	Best	1	6	Dims down to 10%
	Legrand	Maestro	MALV-600	Best	1	6	Dims down to 1%
Universal	Legrand	Harmony	DLV703-PW	Best	1	6	Dims down to 18%
		Adorne SoftTap	ADTP703TU	Best	1	6	Dims down to 18%
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 10%
		Harmony	H703PTUTC	Best	1	6	Dims down to 20%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 20%
	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 15%	
	Cooper	Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 5%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 5%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

### Overall Rating

<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when
<b>Low End (L.E.) Dead Travel</b>	the slider can be moved without affecting the light level.

### Contact Information:

Bulbrite Industries Inc.  
145 West Commercial Avenue  
Moonachie, New Jersey 07074  
PHONE: 1-800-528-5555  
FAX: 1-800-441-7708  
Email: ProductSupport@bulbrite.com  
©2017 Bulbrite Industries Inc.  
All Rights Reserved.