



**Dimmer Compatibility Guide**

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	774138	774139	774140	774141
<b>Item Number:</b>	LED8T18/27K/FIL/2/JA8	LED8T18/30K/FIL/2/JA8	LED8A19/27K/FIL/2/JA8	LED8A19/30K/FIL/2/JA8
<b>Ordering Code:</b>				

		Lamps per Dimmer					
Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes	
				Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IP106	Best	1	6	Dims down to 14%
		SureSlide	6633-P	Best	1	6	Dims down to 1%
	Vizia	VP106-1LZ		Good	2	6	Dims down to 4%
		Toggle	TG-600	Best	1	6	Dims down to 9%
	Lutron	Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Best	1	6	Dims down to 6%
		Titan	CT073-PW	Best	1	6	Dims down to 15%
	Legrand	Harmony	D703-PTC	Best	1	6	Dims down to 1%
		Harmony	H703-PTC	Best	1	6	Dims down to 2%
CFL/LED	Leviton	IllumaTech	IP106	Best	1	6	Dims down to 1%
		SureSlide	6674	Best	1	6	Dims down to 1%
	Decora	6672		Best	1	6	Dims down to 6%
		Skylark	CTCL-153	Best	1	6	Dims down to 1%
	Lutron	Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 5%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggle	TGCL-153PH	Best	1	6	Dims down to 1%
	Legrand	Radio RA	RA-200-6CL-PD	Best	1	6	Dims down to 2%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 10%
Harmony		HCL453-PTC	Best	1	6	Dims down to 10%	
Adome Paddle		ADPD453LM2	Bad	1	6	Dims down to 40%	
Electronic Low Voltage	Leviton	Vizia	VPED4	Good	1	6	Dims down to 12%, minor flicker at LE with 1-6
		IllumaTech	IP504	Good	1	6	Dims down to 12%, minor flicker at LE with 1-6
	Decora	6615-P		Bad	1	6	
		Skylark Countour	CTELV-300P	Good	1	6	Dims down to 12%, minor flicker at LE with 1-6
	Lutron	Diva	DVELV-300P	Good	1	6	Dims down to 8%, minor flicker at LE with 1-6
		Maestro	MAELV-600	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6
		Skylark	SELV-300P	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6
		VISRTI	VTEL-600M-W	Best	1	6	Dims down to 12%
	Legrand	Scene Director	SEELV	Good	1	6	Dims down to 30%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 5%
		Decora	6613-P	Best	1	6	Dims down to 2%
	Lutron	Maestro	MALV-600	Good	2	6	Dims down to 5%
		Harmony	DLV703-PW	Best	1	6	Dims down to 20%
Legrand	Titan	CDLV703-PW	Best	1	6	Dims down to 20%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 12%
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A			
	Insteon	SwitchLin Remote Control dimmer		N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6VCL	Best	1	6	Dims down to 5%
	Legrand	Adome touch Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
	Legrand	Adome Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
	GE	ZWAVE	ZW3005	Best	1	6	Dims down to 5%
Universal	Legrand	Adome SoftTap	ADTP703TU	Best	1	6	Dims down to 20%
		Miro Decorator	DR04-W	Not Compatible	1	6	Flash at LE with 1-6
		Harmony	H703PT1C	Best	1	6	Dims down to 20%
	Cooper	Adome Whisper	ADWR700MMTUM2	Best	1	6	Dims down to 1%
		Adome Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
		Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 25%
	Skye	SAL06P-W-K-L	Best	1	6	Dims down to 2%	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
 †May experience "pop-on"; lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	