



145 West Commercial Ave.
Moon Township, PA 15108



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	776626	776627	776628	776629	776612
Item Number:	LEDSB11/27K/FL/E12/3	LEDSB11/30K/FL/E12/3	LEDSA10/27K/FL/E12/3	LEDSA10/30K/FL/E12/3	LEDAG16/27K/FL/M/3
Ordering Code:					

						Lamps per Dimmer		
Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IP06	Best	1	6	Dims down to 0.1%	
		SureSlide	6633-P	Best	1	6	Dims down to 0.1%	
	Lutron	Vizia	VP06-1L2	Good	2	6	Dims down to 0.1%, minor flicker with 1-6	
		Toggle	TG-600	Best	1	6	Dims down to 0.1%	
	Legrand	Divva	DV-600	Best	1	6	Dims down to 0.1%	
		Skylark	S-600PH	Best	1	6	Dims down to 0.1%	
		Maestro	MAW-600	Good	4	6	Dims down to 0.2%	
		Titan	TD703-PW	Good	4	6	Dims down to 0.1%, flicker at LE with 4-5	
		Harmony	HD703-PTC	Good	1	6	Dims down to 0.1%, flicker at Med with 1-3	
		Harmony	HT703-PTC	Good	1	6	Dims down to 0.1%, flicker at HE with 1	
CFL/LED	Leviton	IlumaTech	IP06	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-4	
		SureSlide	6674	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Lutron	Decora	6672	Best	1	6	Dims down to 0.1%	
		Skylark	CTCL-153	Best	1	6	Dims down to 0.1%	
	Legrand	Divva	DVCL-153PL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Maestro	MAEL-153MH	Best	1	6	Dims down to 0.1%	
		Skylark	SCL-153P	Best	1	6	Dims down to 0.1%	
		Toggle	TGCL-153PH	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 0.1%	
		Harmony	DCL453-PTC	Good	2	6	Dims down to 0.1%, minor flicker at LE & Med with 1 & Med 1-2	
Electronic Low Voltage	Leviton	Vizia	VP04	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		IlumaTech	IPED4	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Lutron	Decora	6615-P	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
		Skylark Countour	CTELV-303P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Legrand	Divva	DVVELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Maestro	MAELV-600	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Skylark	SELVB-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		WERTI	WTEL-600M-W	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
		Scene Director	SCELV	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
		Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	3	6
Decora	6613-P			Good	1	6	Dims down to 1%, flicker at HE with 1-3	
Lutron	Maestro		MALV-600	Bad	5	6	Dims down to 1%	
	Harmony		DLV703-PW	Good	1	6	Dims down to 10%, flicker at LE with 1-6	
Legrand	Titan		CDLV703-PW	Good	1	6	Dims down to 10%, flicker at LE with 1-6	
	Smart Dimmer		Leviton	Decora Delta (Bluetooth)	DDMK1-BL2	Good	1	6
Leviton			Decora Smart Wi-Fi	DKHD-1BZ	N/A			
Insteon			SwitchLin Remote Control dimmer		N/A			
Lutron			Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6
Legrand			Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
Legrand		Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A				
Universal	Leviton	GE	Z-WAVE	ZW3005	Good		Dims down to 10%, minor flicker at LE with 2-6	
		Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 1%	
	Lutron	Miro Decorator	DRD4-W	Good	1	6	Dims down to 1%, flicker at LE with 1-3	
		Harmony	H703PTUTC	Best	1	6	Dims down to 1%	
	Cooper	Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 0.1%	
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 0.1%	
	Legrand	Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6	
		Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Bulbrite Industries, Inc.
 145 West Commercial Avenue
 Moon Township, New Jersey 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries, Inc.
 All Rights Reserved.

