



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:

Item Number: 776880
Ordering Code: LED2T6/27K/FIL/E12/3

Item Number: 776804
Ordering Code: LED2T6/22K/FIL-NOS/3

Lamps per Dimmer

| | Manufacturer | Product | Model Number | Overall Rating | Lamps per Dimmer | | Notes |
|---|----------------------|------------------------------------|----------------------------|----------------|---------------------|--|---|
| | | | | | Recommended Minimum | Maximum Tested* | |
| Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers) | Leviton | IllumaTech | IPI06 | Best | 1 | 6 | Dims down to 0.1% with 1-6, minor flicker at Med with 1 |
| | | SureSlide | 6633-P | Best | 1 | 6 | Dims down to 0.1% with 1-6, minor flicker at HE with 1 |
| | | Vizia | VPI06-1LZ | Bad | 1 | 6 | Dims down to 0.1% with 1-6, minor flicker at Med with 1 & LE with 2-4 |
| | Lutron | Toggle | TG-600 | Good | 1 | 6 | Dims down to 0.1% with 1-6, minor flicker at Med with 1-6 |
| | | Diva | DV-600 | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | Skylark | S-600 | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | Maestro | MAW-600 | Bad | 5 | 6 | Dims down to 1% with 5-6, |
| | Legrand | Titan | CD703-PW | Good | 1 | 6 | Dims down to 0.1% with 1-6, minor flicker at HE with 1-4 |
| | | Harmony | D703-PTC | Good | 1 | 6 | Dims down to 0.1% with 1-6, minor flicker at HE with 1-4 |
| | | Harmony | H703-PTC | Good | 1 | 6 | Dims down to 0.1% with 1-6, minor flicker at HE with 1-4 |
| CFL/LED | Leviton | IllumaTech | IPL06 | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Sureslide | 6674 | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Decora | 6672 | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | Lutron | Skylark | CTCL-153 | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Diva | DVCL-153PL | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Maestro | MACL-153MLH | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Skylark | SCL-153P | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Toggle | TGCL-153PH | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Radio RA | RA2RR-6CL-PD | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | Legrand | Harmony | DCL453-PTC | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Harmony | HCL453PTC | Best | 1 | 6 | Dims down to 0.1% with 1-6, |
| | | Adorne Paddle | ADPD453LM2 | Best | 1 | 6 | Dims down to 2% with 1-6, |
| Electronic Low Voltage | Leviton | Vizia | VPE04 | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | IllumaTech | IPE04 | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | Decora | 6615-P | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | Lutron | Skylark Countour | CTELV-303P | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | Diva | DVELV-300P | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | Maestro | MAELV-600 | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | Skylark | SELVB-300P | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | VIERTI | VTEL-600M-W | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | | Scene Director | SCELV | Best | 1 | 6 | Dims down to 0.1% with 1-6 |
| | Magnetic Low Voltage | Leviton | Vizia | VPM-06 | Good | 2 | 6 |
| Decora | | | 6613-P | Good | 1 | 6 | Dims down to 0.1% with 1-6, Minor flicker at Med with 1 |
| Lutron | | Maestro | MALV-600 | Not Compatible | 5 | 6 | Does not turn on with 1-6 |
| | | Harmony | DLV703-PW | Good | 1 | 6 | Dims down to 0.1% with 1-6, Minor flicker at Med with 1 -2 |
| Legrand | Titan | CDLV703-PW | Good | 1 | 6 | Dims down to 0.1% with 1-6, Minor flicker at Med with 1 -4 | |
| | Smart Dimmer | Leviton | Decora Digital (Bluetooth) | DDMX1-BLZ | Best | 1 | 6 |
| Leviton | | Decora Smart Wi-Fi | DX6HD-1BZ | | | | |
| Insteon | | SwitchLin Remote Control dimmer | | | | | |
| Lutron | | Caseta Wireless smart dimmer Wi-Fi | PD-6WCL | Good | 1 | 6 | Dims down to 1% with 1-6, minor flicker at LE with 1-6 |
| Legrand | | Adorne touch Wi-Fi TRU Universal | ADTH700RMTUW1 | | | | |
| Legrand | | Adorne Sof Tap Wi-Fi TRU Universal | ADTP700RMTUW1 | | | | |
| GE | | Z WAVE | ZW3005 | Best | 1 | 6 | Dims down to 1% with 1-6 |
| Universal | Legrand | Adorne SoftTap | ADTP703TU | Best | 1 | 6 | Dims down to 1% with 1-6 |
| | | Miro Decorator | DRD4-W | Best | 1 | 6 | Dims down to 1% with 1-6, |
| | | Harmony | H703PTUTC | Good | 1 | 6 | Dims down to 7% with 1-6, minor flicker at LE with 1-4 |
| | | Adorne Whisper | ADWR700MMTUW2 | Best | 1 | 6 | Dims down to 1% with 1-6 |
| | | Adorne Touch | ADTH700MMTUM2 | Best | 1 | 6 | Dims down to 1% with 1-6 |
| | Cooper | Decorator | DAL06P-C2-K-L | Best | 1 | 6 | Dims down to 1% with 1-6, |
| | | Skye | SAL06P-W-K-L | Best | 1 | 6 | Dims down to 1% with 1-6 |

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

| | |
|------------------------------------|--|
| Not Compatible | One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off. |
| Bad | One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth. |
| Good | One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise. |
| Best | Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output. |
| High End (H.E.) Dead Travel | Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level. |
| Low End (L.E.) Dead Travel | |

Contact Information:

Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2019 Bulbrite Industries Inc.
All Rights Reserved.