



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: 776617
Item Number: LED8A19/27K/FIL/M/3
Ordering Code:

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	illumaTech	IP06	Best	1	6	Dims down to 10%
		SureSlide	6633-P	Best	1	6	Dims down to 1%
	Vizia		VPI06-1LZ	Good	2	6	Dims down to 5%, 2 minimum load without ghost
		Toggle	TG-600	Best	1	6	Dims down to 5%
	Lutron	Div	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
	Maestro		MAW-600	Good	1	6	Dims down to 5%, minor flicker at LE with 1
		Titan	TD703-PW	Best	1	6	Dims down to 13%
	Legrand	Harmony	D703-PTC	Best	1	6	Dims down to 1%
		Harmony	H703-PTC	Best	1	6	Dims down to 1%
CFL/LED	Leviton	illumaTech	IPLD6	Best	1	6	Dims down to 1%
		SureSlide	6674	Best	1	6	Dims down to 6%
	Decora		6672	Best	1	6	Dims down to 3%
		Skylark Countour	CTCL-153	Best	1	6	Dims down to 1%
	Lutron	Div	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 3%
	Skylark		SCL-153P	Best	1	6	Dims down to 1%
		Toggle	TGCL-153PH	Best	1	6	Dims down to 1%
	Radio RA		RA2R-SCL-PD	Best	1	6	Dims down to 2%
		Harmony	DCL453-PTC	Best	1	6	Dims down to 2%
	Legrand	Harmony	HCL453PTC	Best	1	6	Dims down to 8%
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 30%
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 10%
		illumaTech	IPF04	Best	1	6	Dims down to 10%
	Decora		6615-P	Bad	1	6	Dims down to 40%
		Skylark Countour	CTELV-303P	Best	1	6	Dims down to 10%
	Lutron	Div	DVELV-300P	Best	1	6	Dims down to 10%
		Maestro	MAELV-600	Best	1	6	Dims down to 10%
	Skylark		SELV-300P	Best	1	6	Dims down to 10%
		VISRTI	VTEL-600M-W	Best	1	6	Dims down to 10%
	Legrand	Scene Director	SCELV	Good	1	6	Dims down to 21%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 5%, 2 minimum load without ghost
		Decora	6613-P	Best	1	6	Dims down to 1%
	Lutron	Maestro	MALV-600	Good	2	6	Dims down to 5%, 2 minimum load require
		Harmony	DLV703-PW	Best	1	6	Dims down to 1%
Legrand	Titan	CDLV703-PW	Best	1	6	Dims down to 12%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 15%
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A			
	Insteon	SwitchLin Remote Control dimmer		N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 5%, minor flicker from 5% - 30%
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 5%
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 17%
		Miro Decorator	DRO4-W	Best	1	6	Dims down to 1%
		Harmony	H703PTUC	Best	1	6	Dims down to 20%
	Cooper	Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 1%
		Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 1%
Skyl	SAL06P-W-K-L	Best	1	6	Dims down to 1%		

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on"; lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	