



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:
Item Number: 776613 776614
Ordering Code: LED8A19/27K/FIL/3 LED8A19/30K/FIL/3

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
					Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Best	1	6	Dims down to 10% with 1-6	
		SureSlide	6633-P	Best	1	6	Dims down to 0.1% with 1-6	
		Vizia	VPI06-1LZ	Best	1	6	Dims down to 5% with 1-6	
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 0.1% with 1-6	
		Diva	DV-600	Best	1	6	Dims down to 0.1% with 1-6	
		SkyLark	S-600	Best	1	6	Dims down to 0.1% with 1-6	
		Maestro	MAW-600	Bad	1	6	Dims down to 5% with 1-6	
	Legrand	Titan	CD703-PW	Best	1	6	Dims down to 13% with 1-6	
		Harmony	D703-PTC	Best	1	6	Dims down to 0.1% with 1-6	
	CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dims down to 0.1% with 1-6
Sureslide			6674	Best	1	6	Dims down to 6% with 1-6	
Decora			6672	Best	1	6	Dims down to 2% with 1-6	
Lutron		SkyLark Countour	CTCL-153	Best	1	6	Dims down to 0.1% with 1-6	
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.1% with 1-6	
		Maestro	MACL-153MLH	Best	1	6	Dims down to 4% with 1-6	
		SkyLark	SCL-153P	Best	1	6	Dims down to 0.1% with 1-6	
Legrand		Toggler	TGCL-153PH	Best	1	6	Dims down to 0.1% with 1-6	
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 2% with 1-6	
		Harmony	DCL453-PTC	Best	1	6	Dims down to 1% with 1-6, minor flicker at Med with 2	
Adorne Paddle	Harmony	HCL453PTC	Best	1	6	Dims down to 1% with 1-6, minor flicker at Med with 2		
	Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 25% with 1-6		
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 9% with 1-6	
		IlumaTech	IPE04	Best	1	6	Dims down to 6% with 1-6	
		Decora	6615-P	Bad	1	6	Dims down to 35% with 1-6	
	Lutron	SkyLark Countour	CTELV-303P	Best	1	6	Dims down to 8% with 1-6	
		Diva	DVELV-300P	Best	1	6	Dims down to 8% with 1-6	
		Maestro	MAELV-600	Best	1	6	Dims down to 6% with 1-6	
		SkyLark	SELVB-300P	Best	1	6	Dims down to 8% with 1-6	
	Legrand	VIERTI	VTEL-600M-W	Best	1	6	Dims down to 9% with 1-6	
		Scene Director	SECELV	Good	1	6	Dims down to 21% with 1-6	
	Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	dims down to 4% with 2-6
Decora			6613-P	Best	1	6	Dims down to 1% with 1-6	
Lutron		Maestro	MALV-600	Good	2	6	Dims down to 4% with 2-6	
		Harmony	DLV703-PW	Best	1	6	Dims down to 0.1% with 1-6	
Legrand	Titan	CDLV703-PW	Best	1	6	Dims down to 13% with 1-6		
	Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims down to 15% with 1-6, drop out at LE with 1-6
Leviton		Decora Smart Wi-Fi	DX6HD-1BZ	N/A				
Insteon		SwitchLin Remote Control dimmer		N/A	1	6		
Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 4% with 1-6, minor flicker at LE with 1-6	
Legrand		Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A				
Legrand		Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A				
Universal	Legrand	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 4% with 1-6
		Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 18% with 1-6	
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 2% with 1-6	
		Harmony	H703PTUTC	Good	1	6	Dims down to 21% with 1-6	
	Cooper	Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 0.5% with 1-6	
		Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 0.5% with 1-6	
Decorators	DAL06P-C2-K-L	Best	1	6	Dims down to 0.1% with 1-6			
Skye	SAL06P-W-K-L	Best	1	6	Dims down to 0.1% with 1-6			

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (L.E.) Dead Travel	

Contact information:
 Bulbrite Industries Inc.
 145 West Commercial Avenue
 Moonachie, New Jersey 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708
 Email: ProductSupport@bulbrite.com
 ©2017 Bulbrite Industries Inc.
 All Rights Reserved.