

oduct Family Name: N em Number: dering Code:		DIEAS		Compatibility Gui			
m Number:	77		E NOTE: Compatibility list is based upon testing con	ducted by the manufacturer in a lab simu	ulated environment. Actual results may vary	•	
			71410 771411	771412	771413	77141	4
			/D-SN LED6PAR16NF25/60/827/D				
					Lamps per	Dimmer	*Not on short neck
	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
		IllumaTech	IP106	Good	1	6	Minor flicker at LE with 1-6, dims down 10%
	Leviton	SureSlide	6633-P	Good	1	6	Minor flicker at LE with 1-6 , dims down 10%
-		Vizia	VPI06-1LZ	Not Compatible	1	6	Does not turn off with 1-6
		Toggler	TG-600	Good	1	6	Minor flicker LE with 1-6 , dims down 10%
andescent/Halogen (Triac/Phase	Lutron	Diva	DV-600	Good	1	6	Minor flicker LE with 1-6 , dims down 2%
Cut/Leading Edge Dimmers)		Skylark	S-600	Good	1	6	Minor flicker LE with 1-6 , dims down 2%
,		Maestro	MAW-600	Bad	1	6	4+ minimum load , dims down 2%
		Titan	CD703-PW	Bad	1	6	Minor flicker LE with 1-6 & HE 1-3 , dims down to 20% with 1-6
	Legrand	Titan	CDLV703-PW	Good	1	6	Minor flicker with 2 , dims down to 25% with 3-6
	-	Harmony	D703-PTC	Good	1	6	Minor flicker at LE with 1, dims down to 10% with 2-6
		Harmony	H703-PTC	Good	1	б	Minor flicker at HE with 1 , dims down to 15% with 1-6
		IllumaTech	IPL06	Best	1	6	Dims down 2% with 1 and 1% with 2-6
	Leviton	Sureslide	6674	Best	1	6	Dims down 20% with 1-6
		Decora	6672	Best	1	6	Dims down 20% with 1-6
		Diva	DVCL-153PL	Best	1	6	Dims down 1% with 1-6
		Toggler	TGCL-153PH	Best	1	6	Dims down 1% with 1-6
	Lutron	Maestro	MACL-153MLH	Best	1	6	Dims down 10% with 1-6
CFL/LED		Skylark	CTCL-153	Best	1	6	Dims down 1% with 1-6
		Skylark	SCL-153P	Best	1	6	Dims down 1% with 1-6
		Radio RA	RA2RR-6CL-PD	Good	1	6	Minor flicker at LE with 1-6, dims down to 10%
		Harmony	DCL453-PTC	Best	1	6	Dims down 1% with 1-6
	Legrand	Harmony	HCL453PTC	Good	1	6	Dims down 30% with 1-6
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down 30% with 1-6
Electronic Low Voltage	Leviter.	Vizia	VPE04	Good	1	6	Minor flicker at HE 1-6 , dims down 5%
	Leviton	IllumaTech	IPE04	Good	1	6	Minor flicker at HE 1-6 , dims down 5%
		Decora Skylark	6615-P SELVB-300P	Bad Good	1	6	Flicker at Med 1-6, dims down 50% Minor flicker at Med 1-6, dims down 20%
		Skylark Countour	CTELV-303P	Good	1	6	Minor flicker at HE 1-6 , dims down 20%
	Lutron	Diva	DVELV-300P	Good	1	6	Minor flicker at HE 1-6 , dims down 20%
	Lucion	Maestro	MAELV-600	Good	1	6	Minor flicker at HE 1-6 , dims down 20%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down 20% with 1-6
	Legrand	Scene Director	SCELV	Good	1	6	Dims down 30% with 1-6
	Leviton	Vizia	VPM-06	Bad	1	6	3+ minimum load, dims down 10%
		Decora	6613-P	Best	1	6	Dims down 10% 1-6
Magentic Low Voltage	Lutron	Maestro	MALV-600	Good	1	6	2+ minimum load , dims down 25%
Magentic Low Voltage		Harmony	DLV703-PW	Best	1	6	Dims down 10% 1-6
Magentic Low Voltage	Legrand			Cood	1	6	Dime down 20% 1.6
Magentic Low Voltage	Legrand	Adama Coftan	ADTP703TU	Good	L	6	Dims down 30% 1-6
Magentic Low Voltage	Legrand	Adorne SofTap Miro Decorator		Good	1	E	Minor flicker I E with 1-6 dime down 10%
Magentic Low Voltage		Miro Decorator	DRD4-W	Good	1	6	Minor flicker LE with 1-6 , dims down 10%
	Legrand	Miro Decorator Harmony	H703PTUTC	Good	1 1 1	6	Dims down 30% 1-6
Magentic Low Voltage Universal		Miro Decorator Harmony Adorne Whisper	H703PTUTC ADWR700MMTUW2	Good Best	1 1 1 1	6 6 6	Dims down 30% 1-6 Dims down 5% 1-6
	Legrand	Miro Decorator Harmony Adorne Whisper Adorne Touch	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2	Good Best Best	1 1 1 1 1 1	6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6
		Miro Decorator Harmony Adorne Whisper Adorne Touch	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2	Good Best Best	1 1 1 1 1	6 6 6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6
	Legrand Cooper ditional lamps may work with your turned on immediately to their mir	Miro Decorator Harmony Adorne Whisper Adorne Touch Decorator Skye dimmer system. For maximum capac himum level. The slider needs to be read	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L SAL06P-W-K-L city please consult dimmer manufacturer aised above the minimum light level for t	Good Best Best Good Good r.	1 1 1 1 1 1 1 1	6 6 6	Dims down 30% 1-6 Dims down 5% 1-6
Universal kimum Tested (Lamps per Dimmer) - Add v experience "pop-on", lights cannot be t	Legrand Cooper ditional lamps may work with your turned on immediately to their mir	Miro Decorator Harmony Adorne Whisper Adorne Touch Decorator Skye dimmer system. For maximum capac himum level. The slider needs to be read	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L SAL06P-W-K-L city please consult dimmer manufacturer aised above the minimum light level for t	Good Best Best Good Good r.	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	6 6 6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6 Dims down to 30% 1-6
Universal imum Tested (Lamps per Dimmer) - Add experience "pop-on", lights cannot be t initially off. Then, the slider can be low rall Rating	Legrand Cooper ditional lamps may work with your turned on immediately to their mir ered to get to a lower light level; t	Miro Decorator Harmony Adorne Whisper Adorne Touch Decorator Skye dimmer system. For maximum capac nimum level. The slider needs to be ra he dimmer cannot be turned on to ju	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L SAL06P-W-K-L city please consult dimmer manufacturer aised above the minimum light level for t	Good Best Best Good Good r. the lights to first turn on if they	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	6 6 6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6 Dims down to 30% 1-6
Universal imum Tested (Lamps per Dimmer) - Add experience "pop-on", lights cannot be t initially off. Then, the slider can be low all Rating Compatible C	Legrand Cooper ditional lamps may work with your turned on immediately to their mir ered to get to a lower light level; t One or more of the following ok	Miro Decorator Harmony Adorne Whisper Adorne Touch Decorator Skye dimmer system. For maximum capae nimum level. The slider needs to be rate he dimmer cannot be turned on to ju oserved: Major flickering at various oserved: Some flickering observed	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L SAL06P-W-K-L city please consult dimmer manufacturer aised above the minimum light level for t ist the minimum level. us points, significant audible noise, n d at various points, audible noise ma	Good Best Best Good Good r. the lights to first turn on if they no dimming range, does not t ay be present, dimming not sr	mooth.	6 6 6 6 6 6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6 Dims down to 30% 1-6 Minor flicker LE with 1-6 , dims down 10%
Universal imum Tested (Lamps per Dimmer) - Add experience "pop-on", lights cannot be t initially off. Then, the slider can be low all Rating compatible C	Legrand Cooper ditional lamps may work with your turned on immediately to their mir ered to get to a lower light level; to One or more of the following of One or more of the following of One or more of the following of	Miro Decorator Harmony Adorne Whisper Adorne Touch Decorator Skye dimmer system. For maximum capac himum level. The slider needs to be rate he dimmer cannot be turned on to ju oserved: Major flickering at various pserved: Some flickering observed pserved: Minor flickering at some	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L SAL06P-W-K-L city please consult dimmer manufacturer aised above the minimum light level for t ist the minimum level. us points, significant audible noise, n d at various points, audible noise ma point may exist. Dead travel may ex	Good Best Best Good Good r. the lights to first turn on if they no dimming range, does not t ay be present, dimming not sr	mooth.	6 6 6 6 6 6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6 Dims down to 30% 1-6 Minor flicker LE with 1-6 , dims down 10%
Universal mum Tested (Lamps per Dimmer) - Add experience "pop-on", lights cannot be t initially off. Then, the slider can be low all Rating compatible	Legrand Cooper ditional lamps may work with your turned on immediately to their mir ered to get to a lower light level; ti One or more of the following ok One or more of the following ok One or more of the following ok Due or more of the following ok	Miro Decorator Harmony Adorne Whisper Adorne Touch Decorator Skye dimmer system. For maximum capac nimum level. The slider needs to be rational he dimmer cannot be turned on to ju oserved: Major flickering at various oserved: Some flickering observed oserved: Minor flickering at some of the time not visible. Minor au	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L SAL06P-W-K-L city please consult dimmer manufacturer aised above the minimum light level for t us points, significant audible noise, n d at various points, audible noise ma point may exist. Dead travel may ex dible noise.	Good Best Best Good r. the lights to first turn on if they no dimming range, does not t ay be present, dimming not si xist, which means there may l	mooth. be periods of time when the sli	6 6 6 6 6 6 6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6 Dims down to 30% 1-6 Minor flicker LE with 1-6 , dims down 10%
Universal imum Tested (Lamps per Dimmer) - Add experience "pop-on", lights cannot be t initially off. Then, the slider can be low rall Rating Compatible C I	Legrand Cooper ditional lamps may work with your turned on immediately to their mir ered to get to a lower light level; ti One or more of the following ok One or more of the following ok One or more of the following ok Due or more of the following ok	Miro Decorator Harmony Adorne Whisper Adorne Touch Decorator Skye dimmer system. For maximum capac nimum level. The slider needs to be rational he dimmer cannot be turned on to ju oserved: Major flickering at various oserved: Some flickering observed oserved: Minor flickering at some of the time not visible. Minor au	H703PTUTC ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L SAL06P-W-K-L city please consult dimmer manufacturer aised above the minimum light level for t us points, significant audible noise, n d at various points, audible noise ma point may exist. Dead travel may ex	Good Best Best Good r. the lights to first turn on if they no dimming range, does not t ay be present, dimming not si xist, which means there may l	mooth. be periods of time when the sli	6 6 6 6 6 6 6	Dims down 30% 1-6 Dims down 5% 1-6 Dims down 5% 1-6 Dims down to 30% 1-6