



145 West Commercial Ave. Moonachie, NJ 07075

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility is based upon usage conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:	778853	778808	778908
Item Number:	LED379/27K/FIL/3	LED379/22K/FIL-NOS/3	LED379/21K/FIL-NOS/3
Ordering Code:			
Item Number:			
Ordering Code:			

Lamps per Dimmer

Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum		Maximum Tested*	Notes	
				1	2			
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	HumiTech	HD5	Best	1	6	dims down to 1%	
		SceneSlide	SE33-P	Best	1	6	dims down to 1%	
	Lutron	Vista	VPO6-IL2	Good	3	6	dims down to 1%	
		Taggart	TG-600	Best	1	6	dims down to 1%	
	Legrand	Decora	DLV-600	Best	1	6	dims down to 1%	
		Sayark	S-600	Best	1	6	dims down to 1%	
		Maestro	MAV-600	Not Compatible	1	6	does not turn on with 1-6	
		Titan	TLV703-PW	Best	1	6	dims down to 1%	
		Harmony	H303-PTC	Best	1	6	dims down to 1%	
		Harmony	H303-PTC	Good	1	6	dims down to 1%, flicker at Mod with 1-3	
CFU/LED	Leviton	HumiTech	HD6	Best	1	6	dims down to 1%	
		SceneSlide	SE74	Best	1	6	dims down to 1%	
	Decora	DLV3	Best	1	6	dims down to 1%		
		DLV4	Best	1	6	dims down to 1%		
	Lutron	Decora Slide	DS-36	Best	1	6	dims down to 1%	
		Sayark	STCL-153	Best	1	6	dims down to 1%	
	Legrand	Deca	DLVCL-153PL	Best	1	6	dims down to 1%	
		Maestro	MAEL-153MLH	Best	1	6	dims down to 1%	
		Taggart	TGCL-153P	Best	1	6	dims down to 1%	
		Radio RA	RAZR-6CL-PO	Best	1	6	dims down to 1%	
		Harmony	HCL45-PTC	Best	1	6	dims down to 1%	
		Harmony	HCL45-PTC	Best	1	6	dims down to 1%	
	Electronic Low Voltage	Leviton	Vista	VPE6A	Best	1	6	dims down to 1%
			HumiTech	HE6A	Best	1	6	dims down to 1%
		Lutron	Decora	DE15-P	Bad	1	6	dims down to 100%
			Sayark Countour	SELV-300P	Best	1	6	dims down to 1%
		Legrand	Deca	DLVCL-300P	Best	1	6	dims down to 1%
			Maestro	MAELV-600	Best	1	6	dims down to 1%
Sayark			SELV-300P	Best	1	6	dims down to 1%	
VISTA			VTEC-600A-W	Best	1	6	dims down to 1%	
Scene Director			SDCLV	Bad	1	6	dims down to 1%	
Magnetic Low Voltage			Leviton	Vista	VPM-60	Good	2	6
	Decora	DE13-P		Best	1	6	dims down to 1%	
	Lutron	Maestro	MAV-600	Bad	6	6	dims down to 1%	
		Harmony	HLV703-PW	Best	1	6	dims down to 1%	
	Legrand	Titan	TLV703-PW	Best	1	6	dims down to 1%	
		Smart Dimmer	Leviton	Decora Digital (Bluebooth)	DRAMA-SL2	Best	1	6
	Leviton		Decora Smart 2-Wave Technology	DS2HD	Best	1	6	dims down to 7%
	Lutron		Caseta Wireless smart dimmer Wi-Fi	FD-WND01	Best	1	6	dims down to 1%
	Lutron		Caseta Wireless smart dimmer Wi-Fi	FD-EM-CL	Good	1	6	dims down to 1%, shimmer at LE with 1-6
	Legrand		Adorne touch Wi-Fi TRU Universal	ADT5708M-TLW1				
Legrand	Adorne Soft Tap Wi-Fi TRU Universal		ADT5708M-TLW1					
Universal	Legrand	Adorne SoftTap	ADT5708TU	Best	1	6	dims down to 1%	
		Adorne Dimmer	ADDA-W	Best	1	6	dims down to 1%	
	Cooper	Harmony	H303-PTC	Best	1	6	dims down to 1%	
		Adorne Whispur	ADW708M-TLW2	Best	1	6	dims down to 1%	
	Cooper	Adorne Touch	ADT5708M-TLW2	Not Compatible	1	6	does not turn on with 1-6	
		Decorador	DADEP-C2-K-L	Best	1	6	dims down to 1%	
	Cooper	Slave	SLAVE-W-K-L	Best	1	6	dims down to 1%	

*Maximum Tested Lamps per Dimmer - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
 †May experience "pop on" lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating

Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.

High End (H.E.) Dead Travel - Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

Contact Information:
 Bulbrite Industries Inc.
 145 West Commercial Avenue Moonachie, New Jersey 07075
 PHONE: 1-800-528-0155 FAX: 1-800-443-7708
 Email: ProductSupport@bulbrite.com
 ©2019 Bulbrite Industries Inc.
 All Rights Reserved.