



# Value Select MR Family

## MODEL

Model: 6MR16DIM/xxxFL35/35W/R  
 6MR16DIM/xxxFL35  
 6MR16DIM/xxxFL35/R  
 6GU10DIM/xxxFL35/R  
 6PAR16DIM/xxxFL35/R

Where xxx means 824-965 which indicates CRI and color temperature



## ELECTRONIC DIMMER SWITCH COMPATIBILITY

Model: 6MR16DIM/xxxFL35/35W/R

Brand	Series	Model	Load (w)	Hatch																																											
				RS12-60M-LED (DC1340)						RS12-60M (DC1124LED)						RS12-60M-LED (DC1323)						RS12-60M (DC1130)						RS12-80M (DC5209)						RS12-80M (DC1412)						RS12-30M-LED (DC1418)					RS12-15M-LED (DC1538K)		
				1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	6	1	2	3	4	5	1	2							
Lutron	Toggler	6B38	600	X						X						X						X						X						X					X								
	Nova	NTELV-300	300	OK W/Noise						OK						OK W/Noise						X						X						OK W/Noise					OK W/Noise								
Leviton	Decora	6615P	1000	X						X						X						X						X						X					X								

## MAGNETIC DIMMER SWITCH COMPATIBILITY

Brand	Series	Model	Load (w)	Dimmability (# of lamps)											
				HALO CAN		ELCO		Juno		NORA		ESBCO		ELG	
				1	2	1	2	1	2	1	2	1	2	1	2
Lutron	Abella	ABLV-1000M	1000	X		30-100%		X		X		X		X	
	Maestro	MALV-600	600	OK		OK		OK		X		X		X	
	Skylark	SLV-600P	600	OK		X		20-100%		OK		OK		OK	
Legrand	Harmony	H703PTU	600	X		X		X		X		X		X	
	Adorne	ADTP703TU	700	OK		OK		OK		OK		OK		OK	
Leviton	Sure Slide	6613-P	600	OK		OK		X		OK		OK		OK	
	VIZA+	VPM10-1LX	1000	X		OK		X		X		X		OK	
Cooper	Devine	DAL06P	300	X		X		X		X		OK		X	
	Aspire	9536	600	X		X		X		X		X		X	

OK- Fully Compatible  
 X - Not Compatible

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



# Value Select MR Family

## MAGNETIC DIMMER SWITCH COMPATIBILITY

Model: 6MR16DIM/xxxFL35 6MR16DIM/xxxFL35/R

Brand	Series	Model	Load (w)	Dimmability (# of lamps)											
				HALO CAN		ELCO		Juno		NORA		ESBCO		ELG	
				1	2	1	2	1	2	1	2	1	2	1	2
Lutron	Abella	ABLV-1000M	1000	X		15-100%*		X		X		X		OK**	
	Maestro	MALV-600	600	X		X		X		OK**		X		X	
	Skylark	SLV-600P	600	X		OK		OK		15-100%**		X		15-100%**	
Legrand	Harmony	H703PTU	600	X		15-100%		15-100%		OK		X		OK**	
	Adorne	ADTP703TU	700	X		OK		OK		OK		X		OK**	
Leviton	Sure Slide	6613-P	600	X		OK		OK		OK		X		X	
	VIZA+	VPM10-1LX	1000	X		OK		X		OK**		X		OK**	
Cooper	Devine	DAL06P	300	X		X		OK		15-100%**		X		OK**	
	Aspire	9536	600	X		X		X		X		X		X	

\*Minimum 2 lamps

\*\*Minimum 3 lamps

OK- Fully Compatible

X - Not Compatible

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



# Value Select MR Family

## DIMMER COMPATIBILITY

6GU10DIM/xxxFL35/R

Brand	Series	Model	Load (W)	Dimmability
Lutron	Rotary	D-600P	600	OK
	Diva	DV-600PR	600	10-80%
	Skylark Contour	CT-600P	600	10-80%
	Toggler	TG-600P	600	X
	Maestro	MA-600	600	X
	Skylark	S-600P	600	OK
	Skylark Contour	CTCL-153P	150	OK
	Toggler	TGCL-153P	150	OK
	Diva	DVCL-153P	150	OK
	Maestro Wireless	MRF2-6CL	150	X
	Ariadni	AYCL-153P	150	OK
Legrand	Harmony	HCL453P	450	OK
	Harmony	H703PTU	450	OK
	Adorne	ADPD453L	450	X
	Adorne	ADTP703TU	700	X
Leviton	Sureslide Decora	6674	600	15-85%
	Sureslide	6633	600	OK
	Trimatron	6602	600	OK
	Vizia+	VP106	600	X
Cooper	Devine	DAL06P	300	X
	ASPIRE	9540	300	30-100%
	ASPIRE	9536	1000	X

OK- Fully Compatible

X - Not Compatible

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.



# Value Select MR Family

## DIMMER COMPATIBILITY

6PAR16DIM/xxxFL35/R

Brand	Series	Model	Load (W)	Dimmability
Lutron	Rotary	D-600P	600	OK
	Diva	DV-600PR	600	10-80%
	Skylark Contour	CT-600P	600	10-80%
	Toggler	TG-600P	600	X
	Maestro	MA-600	600	X
	Skylark	S-600P	600	OK
	Skylark Contour	CTCL-153P	150	OK
	Toggler	TGCL-153P	150	OK
	Diva	DVCL-153P	150	OK
	Maestro Wireless	MRF2-6CL	150	X
	Ariadni	AYCL-153P	150	OK
Legrand	Harmony	HCL453P	450	OK
	Harmony	H703PTU	450	OK
	Adorne	ADPD453L	450	X
	Adorne	ADTP703TU	700	X
Leviton	Sureslide Decora	6674	600	15-85%
	Sureslide	6633	600	OK
	Trimatron	6602	600	OK
	Vizia+	VP106	600	X
Cooper	Devine	DAL06P	300	X
	ASPIRE	9540	300	30-100%
	ASPIRE	9536	1000	X

OK- Fully Compatible

X - Not Compatible

GREEN CREATIVE has provided this dimmer switch compatibility chart for guidance when selecting a dimmer and lamp combination. Our lamps were tested for compatibility with the above listed dimmers. Dimmers that do not appear on the chart might still be compatible but have not been tested. All testing has been performed with a stable main supply. The quality of the local main, existing installation and wiring, as well as different manufacturer versions of the above dimmers may affect dimming performance. Since no assurance can be provided regarding these factors, it is a general recommendation to perform a test on-site prior to installing the LED lamps.