



145 West Commercial Ave. Moonachie, NJ 07074

### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:

Item Number:	776880	776804	776904	776891
Ordering Code:	LEDZT6/2TK/PI/L/E12/3	LEDZT6/22K/PI/L-NOS/3	LEDZT6/21K/PI/L-NOS/3	LEDZT6/30K/PI/L/3
Item Number:				
Ordering Code:				

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes		
					Recommended Minimum	Maximum Tested*			
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	illumaTech	IP106	Best	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1		
		Sureslide	6633-P	Best	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1		
		Viola	V705-1L2	Bad	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1 & LE with 2-4		
		Toggle	TG-600	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at Med with 1-6		
		Divva	DV-600	Best	1	6	Dims down to 0.1% with 1-6		
	Lutron	SkyLark	S-600	Best	1	6	Dims down to 0.1% with 1-6		
		Maestro	MAW-600	Bad	5	6	Dims down to 1% with 5-6,		
		Titan	CD703-PW	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1-4		
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1-4		
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1% with 1-6, minor flicker at HE with 1-4		
CFL/LED	Leviton	illumaTech	IP106	Best	1	6	Dims down to 0.1% with 1-6,		
		Sureslide	6674	Best	1	6	Dims down to 0.1% with 1-6,		
		Decora	6672	Best	1	6	Dims down to 0.1% with 1-6,		
		SkyLark	CTL-153	Best	1	6	Dims down to 0.1% with 1-6,		
		Divva	DVCL-153PL	Best	1	6	Dims down to 0.1% with 1-6,		
	Lutron	Maestro	MAEL-153MH	Best	1	6	Dims down to 0.1% with 1-6,		
		SkyLark	SCL-153P	Best	1	6	Dims down to 0.1% with 1-6,		
		Toggle	TGCL-153PH	Best	1	6	Dims down to 0.1% with 1-6,		
		Radio RA	RA2R8-6CL-PD	Best	1	6	Dims down to 0.1% with 1-6,		
		Harmony	DCL453-PTC	Best	1	6	Dims down to 0.1% with 1-6,		
	Legrand	Harmony	HCL453PTC	Best	1	6	Dims down to 0.1% with 1-6,		
		Adorne Paddle	ADPD453LMZ	Best	1	6	Dims down to 2% with 1-6,		
		Electronic Low Voltage	Leviton	Viola	VPE04	Best	1	6	Dims down to 0.1% with 1-6
				illumaTech	IP104	Best	1	6	Dims down to 0.1% with 1-6
				Decora	6615-P	Best	1	6	Dims down to 0.1% with 1-6
SkyLark Countour	CTLV-303P			Best	1	6	Dims down to 0.1% with 1-6		
Divva	DV1V-300P			Best	1	6	Dims down to 0.1% with 1-6		
Lutron	Maestro		MAELV-600	Best	1	6	Dims down to 0.1% with 1-6		
	SkyLark		SCLV-300P	Best	1	6	Dims down to 0.1% with 1-6		
	Viola		VTEL-600M-W	Best	1	6	Dims down to 0.1% with 1-6		
	VTELT		VTEL-600M-W	Best	1	6	Dims down to 0.1% with 1-6		
	Scene Director		SCLV	Best	1	6	Dims down to 0.1% with 1-6		
Magnetic Low Voltage	Leviton	Viola	VPM-06	Good	2	6	Dims down to 1% with 1-6, Minor flicker at HE with 1-4		
		Decora	6613-P	Good	1	6	Dims down to 0.1% with 1-6, Minor flicker at Med with 1		
	Lutron	Maestro	MALV-600	Not Compatible	5	6	Does not turn on with 1-6		
		Harmony	DLV703-PW	Good	1	6	Dims down to 0.1% with 1-6, Minor flicker at Med with 1-2		
	Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 0.1% with 1-6, Minor flicker at Med with 1-4		
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1% with 1-6		
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ						
	Insteon	SwitchIn Remote Control dimmer							
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 1% with 1-6, minor flicker at LE with 1-6		
	Legrand	Adorne Touch Wi-Fi TRU Universal	ADTN700RMTUW1						
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTF700RMTUW1						
Universal	Legrand	Z-WAVE	ZW3005	Best	1	6	Dims down to 1% with 1-6		
		Adorne SoftTap	ADTF7003TU	Best	1	6	Dims down to 1% with 1-6		
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 1% with 1-6,		
		Harmony	H703PTUTC	Good	1	6	Dims down to 7% with 1-6, minor flicker at LE with 1-4		
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1% with 1-6		
	Cooper	Adorne Touch	ADTN700MMTUW2	Best	1	6	Dims down to 1% with 1-6		
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 1% with 1-6,		
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 1% with 1-6,		
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1% with 1-6		
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1% with 1-6		

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

**Overall Rating**

<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
<b>Low End (L.E.) Dead Travel</b>	

Contact Information:  
 Bulbrite Industries Inc.  
 145 West Commercial Avenue Moonachie, New Jersey 07074  
 PHONE: 1-800-528-5555 FAX: 1-800-441-7708  
 Email: ProductSupport@bulbrite.com  
 ©2019 Bulbrite Industries Inc. All Rights Reserved.