

# LOW-VOLTAGE PENDANTS

## Playa Pendant

### DESCRIPTION

Elegant multi-toned cylindrical shade comprised of natural shell panels. The shells are burnished to remove rough edges, meticulously polished, cut to size, and carefully adhered by hand to an inner glass cylinder. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt replaceable 500 lumen 80 CRI 3000K LED SORAA® module and six feet of field-cuttable suspension cable. Works with SORAA.

### INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system.

### ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook

### WEIGHT

1.5lb / 0.68kg ±



brown



brown



natural



white

### ORDERING INFORMATION

700	SYSTEM	PLA	COLOR	FINISH	LAMP
FJ	FREEJACK		<b>B</b> BROWN	<b>Z</b> ANTIQUE BRONZE	12 VOLT HALOGEN
KL	KABLE LITE		<b>C</b> CHROME	<b>C</b> CHROME	<b>-LEDS830</b> 12 VOLT LED 80 CRI 3000K
MP	MONOPOINT		<b>N</b> NATURAL	<b>S</b> SATIN NICKEL	<b>-24</b> 24 VOLT HALOGEN
MO	MONORAIL		<b>W</b> WHITE		
MO2	TWO-CIRCUIT MONORAIL				

Note: Note: MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.

When installing LED option on MO2 only magnetic transformers may be used.



700 \_\_\_\_ PLA \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_



©2016 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.