



lightology.com
866-954-4489
08-04-25

Project: _____

Company: _____

Location: _____ Fixture Type: _____

SPEC #: **GRC1080813**

Approved On: _____ Approved By: _____

35W Emergency Inverter for 4,6,8 Inch Models


By Green Creative

Description

35W Emergency Inverter (field installation)
designed for use with Green Creative Retrofit
Downlights. For use with Innofit and Selectfit 4, 6
and 8 inch models only.



Shown in black



Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	35W
DIMMER	N/A
DIMENSIONS	17.75"W x 2.75"H
BULB NOT INCLUDED	N/A



CLICK TO VIEW PRODUCT

Notes:
