

# Lightology

lightology.com  
866-954-4489  
05-17-26

Project: \_\_\_\_\_  
Company: \_\_\_\_\_  
Location: \_\_\_\_\_ Fixture Type: \_\_\_\_\_  
SPEC #: **WAC1092653**  
Approved On: \_\_\_\_\_ Approved By: \_\_\_\_\_

## 12V Enclosed Electronic Transformer By WAC Lighting



### Description

Low Voltage 120V input/12V output electronic transformer designed to be used as a replacement part for factory installed transformers. Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp. All connections must be made in an enclosure for proper installations. Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer. Note: 1 watt minimum load / 250 watt option includes LED indicator lights and integral push-in terminals. Optional accessories sold separately.



Shown in black

### Specifications

COLOR	N/A
BODY FINISH	Black
WATTAGE	60W
DIMMER	Low Voltage Electronic
DIMENSIONS	6.63"L x 1.63"W x 1.13"H
BULB	N/A



CLICK TO VIEW PRODUCT

Notes: