

Lightology

lightology.com
866-954-4489
10-10-25

Project: _____
Company: _____
Location: _____ Fixture Type: _____
SPEC #: **BPU1303208**
Approved On: _____ Approved By: _____

Buster + Punch Complete Metal Dimmer NEW

By Buster + Punch



Description

The Buster + Punch Complete Dimmer is made from solid metal with a diamond cut knurled knob. Works exclusively with the Buster + Punch range of wall plates, dimmer knobs and detail kits. Operates with a push on/off rotary dimmer action for pinpoint dimming accuracy and can be used with single pole or 3-way circuits. The dimmer module has intelligent load matching to enhance compatibility, while minimizing noise and flicker. It can be used on a lighting circuit that powers dimmable LED, low voltage bulbs, LED drivers and it is optimized for use with all Buster + Punch dimmable light bulbs. The dimmer module has a max load of 250W for LED and 300W halogen or incandescent light sources. Fit this dimmer as the only switch on a single-pole circuit, or to control your lighting from two locations on the same circuit, use this dimmer switch and one 3-way on/off switch. The Complete Dimmer includes push On/Off rotary dimmer module compatible with 3-way switching, wall plate, and detail kit. Dimmer has a 1/8 inch shadow gap when installed. Available with or without a Buster + Punch logo. NOTE: This dimmer module is not a 0-10V dimmer and is not compatible with retractive switches, non-dimmable LED lamps, fluorescent and energy-saving bulbs and tubes, electric motors, and fans. Learn more about Buster + Punch Electricity Collection here.






Specifications

COLOR N/A
BODY FINISH White
WATTAGE 300W
DIMMER N/A
DIMENSIONS 2.75"W x 4.75"H
BULB N/A
COUNTRY OF ORIGIN China



Shown in white

ELECTRICAL SPECIFICATIONS

PARAMETER	VALUE
Supply voltage & Frequency	100 - 120V AC 60Hz
Rating	5-250W. When used with dimmable LED lamps, 10-300W. When used with incandescent lamps, halogen lamps and Low Voltage Incandescent Ballasts
Dimming Technology	 Automatic Detection of Forward Phase and Reverse Phase Dimming mode. User Select also available:
Compatible loads for RP MODE - REVERSE PHASE	 Dimmable LED lighting with compatible Electronic Transformers
	 LV Halogen Lighting with electronic transformers
Compatible loads for FP MODE - FORWARD PHASE	 Incandescent lighting, MV Halogen lamps
	 LV Halogen Lighting with iron-core transformers
Operating Temperature	32° - 95° F
Operating Humidity	10 - 90% R.H.



CLICK TO VIEW PRODUCT

Notes: